



NASoftware Limited
Incorporating InfoSAR

VS IPL

List of Contents

VS IPL/Content [3.1D]

Release 3.1D
May 2013

Chapter 1. Support Functions

1.1 Initialisation and Finalisation

Prototype	Description
<pre>int vsip_init(void * ptr);</pre>	Provides initialisation, allowing the library to allocate and set a global state, and prepare to support the use of VSIPL functionality by the user.
<pre>int vsip_finalize(void * ptr);</pre>	Provides cleanup and releases resources used by VSIPL (if the last of a nested series of calls), allowing the library to guarantee that any resources allocated by <code>vsip_init</code> are no longer in use after the call is complete.
<pre>void Thread_SetParams(vsip_length num_threads, vsip_length max_num_running);</pre>	Allows the library to allocate a number of threads.

1.2 Array and Block Functions

Prototype	Description
<pre>int vsip_Dblockadmit_P(vsip_Dblock_P * block, vsip_scalar_bl update);</pre>	Admit a data block for VSIPL operations. The following instances are supported: <code>vsip_blockadmit_f</code> <code>vsip_blockadmit_d</code> <code>vsip_blockadmit_i</code> <code>vsip_blockadmit_si</code> <code>vsip_cblockadmit_f</code> <code>vsip_cblockadmit_d</code> <code>vsip_cblockadmit_i</code> <code>vsip_cblockadmit_si</code> <code>vsip_blockadmit_bl</code> <code>vsip_blockadmit_vi</code> <code>vsip_blockadmit_mi</code>
<pre>vsip_block_P * vsip_blockbind_P(vsip_scalar_P * user_data, vsip_length num_items, vsip_memory_hint hint);</pre>	Create and bind a VSIPL block to a user-allocated data array. The following instances are supported: <code>vsip_blockbind_f</code> <code>vsip_blockbind_d</code> <code>vsip_blockbind_i</code> <code>vsip_blockbind_si</code> <code>vsip_blockbind_bl</code> <code>vsip_blockbind_vi</code> <code>vsip_blockbind_mi</code>

Prototype	Description
<pre>vsip_cblock_P * vsip_cblockbind_P(vsip_scalar_P * user_data1, vsip_scalar_P * user_data2, vsip_length num_items, vsip_memory_hint hint);</pre>	<p>Create and bind a VSIPL complex block to a user-allocated data array. The following instances are supported:</p> <pre>vsip_cblockbind_f vsip_cblockbind_d vsip_cblockbind_i vsip_cblockbind_si</pre>
<pre>vsip_Dblock_P * vsip_Dblockcreate_P(vsip_length num_items, vsip_memory_hint hint);</pre>	<p>Creates a VSIPL block and binds a (VSIPL-allocated) data array to it. The following instances are supported:</p> <pre>vsip_blockcreate_f vsip_blockcreate_d vsip_blockcreate_i vsip_blockcreate_si vsip_cblockcreate_f vsip_cblockcreate_d vsip_cblockcreate_i vsip_cblockcreate_si vsip_blockcreate_bl vsip_blockcreate_vi vsip_blockcreate_mi</pre>
<pre>void vsip_Dblockdestroy_P(vsip_Dblock_P * block);</pre>	<p>Destroy a VSIPL block object and any memory allocated for it by VSIPL. The following instances are supported:</p> <pre>vsip_blockdestroy_f vsip_blockdestroy_d vsip_blockdestroy_i vsip_blockdestroy_si vsip_cblockdestroy_f vsip_cblockdestroy_d vsip_cblockdestroy_i vsip_cblockdestroy_si vsip_blockdestroy_bl vsip_blockdestroy_vi vsip_blockdestroy_mi</pre>
<pre>vsip_scalar_P * vsip_blockfind_P(const vsip_block_P * block);</pre>	<p>Find the pointer to the data bound to a VSIPL released block object. The following instances are supported:</p> <pre>vsip_blockfind_f vsip_blockfind_d vsip_blockfind_i vsip_blockfind_si vsip_blockfind_bl vsip_blockfind_vi vsip_blockfind_mi</pre>
<pre>void vsip_cblockfind_P(const vsip_cblock_P * block, vsip_scalar_P ** user_data1, vsip_scalar_P ** user_data2);</pre>	<p>Find the pointer(s) to the data bound to a VSIPL released complex block object. The following instances are supported:</p> <pre>vsip_cblockfind_f vsip_cblockfind_d vsip_cblockfind_i vsip_cblockfind_si</pre>

Prototype	Description
<pre>vsip_scalar_P * vsip_blockrebind_P(vsip_block_P * block, vsip_scalar_P * new_data);</pre>	<p>Rebind a VSIPL block to user-specified data. The following instances are supported:</p> <pre>vsip_blockrebind_f vsip_blockrebind_d vsip_blockrebind_i vsip_blockrebind_si vsip_blockrebind_bl vsip_blockrebind_vi vsip_blockrebind_mi</pre>
<pre>void vsip_cblockrebind_P(vsip_cblock_P * block, vsip_scalar_P * new_data1, vsip_scalar_P * new_data2, vsip_scalar_P ** old_data1, vsip_scalar_P ** old_data2);</pre>	<p>Rebind a VSIPL complex block to user-specified data. The following instances are supported:</p> <pre>vsip_cblockrebind_f vsip_cblockrebind_d vsip_cblockrebind_i vsip_cblockrebind_si</pre>
<pre>vsip_scalar_P * vsip_blockrelease_P(vsip_block_P * block, vsip_scalar_bl update);</pre>	<p>Release a VSIPL block for direct user access. The following instances are supported:</p> <pre>vsip_blockrelease_f vsip_blockrelease_d vsip_blockrelease_i vsip_blockrelease_si vsip_blockrelease_bl vsip_blockrelease_vi vsip_blockrelease_mi</pre>
<pre>void vsip_cblockrelease_P(vsip_cblock_P * block, vsip_scalar_bl update, vsip_scalar_P ** user_data1, vsip_scalar_P ** user_data2);</pre>	<p>Release a complex block from VSIPL for direct user access. The following instances are supported:</p> <pre>vsip_cblockrelease_f vsip_cblockrelease_d vsip_cblockrelease_i vsip_cblockrelease_si</pre>
<pre>void vsip_complete(void);</pre>	<p>Force all deferred VSIPL execution to complete.</p>
<pre>vsip_cmplx_mem vsip_cstorage(void);</pre>	<p>Returns the preferred complex storage format for the system.</p>

1.3 Vector View Functions

Prototype	Description
<pre>void vsip_Dvalldestroy_P(vsip_Dvview_P * vector);</pre>	<p>Destroy a vector, its associated block, and any VSIPL data array bound to the block.</p> <p>The following instances are supported:</p> <pre>vsip_valldestroy_f vsip_valldestroy_d vsip_valldestroy_i vsip_valldestroy_si vsip_cvalldestroy_f vsip_cvalldestroy_d vsip_cvalldestroy_i vsip_cvalldestroy_si vsip_valldestroy_bl vsip_valldestroy_vi vsip_valldestroy_mi</pre>
<pre>vsip_Dvview_P * vsip_Dvbind_P(vsip_Dblock_P * block, vsip_offset offset, vsip_stride stride, vsip_length length);</pre>	<p>Create a vector view object and bind it to a block object.</p> <p>The following instances are supported:</p> <pre>vsip_vbind_f vsip_vbind_d vsip_vbind_i vsip_vbind_si vsip_cvbind_f vsip_cvbind_d vsip_cvbind_i vsip_cvbind_si vsip_vbind_bl vsip_vbind_vi vsip_vbind_mi</pre>
<pre>vsip_Dvview_P * vsip_Dvcloneview_P(const vsip_Dvview_P * vector);</pre>	<p>Create a clone of a vector view.</p> <p>The following instances are supported:</p> <pre>vsip_vcloneview_f vsip_vcloneview_d vsip_vcloneview_i vsip_vcloneview_si vsip_cvcloneview_f vsip_cvcloneview_d vsip_cvcloneview_i vsip_cvcloneview_si vsip_vcloneview_bl vsip_vcloneview_vi vsip_vcloneview_mi</pre>
<pre>vsip_Dvview_P * vsip_Dvcreate_P(vsip_length length, vsip_memory_hint hint);</pre>	<p>Creates a block object and a vector view object of the block.</p> <p>The following instances are supported:</p> <pre>vsip_vcreate_f vsip_vcreate_d vsip_vcreate_i vsip_vcreate_si vsip_cvcreate_f vsip_cvcreate_d vsip_cvcreate_i vsip_cvcreate_si vsip_vcreate_bl vsip_vcreate_vi vsip_vcreate_mi</pre>

Prototype	Description
<pre>vsip_Dblock_P * vsip_Dvdestroy_P(vsip_Dvview_P * vector);</pre>	<p>Destroy a vector view object and return a pointer to the associated block object.</p> <p>The following instances are supported:</p> <pre>vsip_vdestroy_f vsip_vdestroy_d vsip_vdestroy_i vsip_vdestroy_si vsip_cvdestroy_f vsip_cvdestroy_d vsip_cvdestroy_i vsip_cvdestroy_si vsip_vdestroy_bl vsip_vdestroy_vi vsip_vdestroy_mi</pre>
<pre>vsip_Dscalar_P vsip_Dvget_P(const vsip_Dvview_P * vector, vsip_index j);</pre>	<p>Get the value of a specified element of a vector view object.</p> <p>The following instances are supported:</p> <pre>vsip_vget_f vsip_vget_d vsip_vget_i vsip_vget_si vsip_cvget_f vsip_cvget_d vsip_cvget_i vsip_cvget_si vsip_vget_bl vsip_vget_vi vsip_vget_mi</pre>
<pre>void vsip_Dvgetattrib_P(const vsip_Dvview_P * vector, vsip_Dvattr_P * attr);</pre>	<p>Return the attributes of a vector view object.</p> <p>The following instances are supported:</p> <pre>vsip_vgetattrib_f vsip_vgetattrib_d vsip_vgetattrib_i vsip_vgetattrib_si vsip_cvgetattrib_f vsip_cvgetattrib_d vsip_cvgetattrib_i vsip_cvgetattrib_si vsip_vgetattrib_bl vsip_vgetattrib_vi vsip_vgetattrib_mi</pre>
<pre>vsip_Dblock_P * vsip_Dvgetblock_P(const vsip_Dvview_P * vector);</pre>	<p>Get the block attribute of a vector view object.</p> <p>The following instances are supported:</p> <pre>vsip_vgetblock_f vsip_vgetblock_d vsip_vgetblock_i vsip_vgetblock_si vsip_cvgetblock_f vsip_cvgetblock_d vsip_cvgetblock_i vsip_cvgetblock_si vsip_vgetblock_bl vsip_vgetblock_vi vsip_vgetblock_mi</pre>

Prototype	Description
<pre>vsip_length vsip_Dvgetlength_P(const vsip_Dvview_P * vector);</pre>	<p>Get the length attribute of a vector view object. The following instances are supported:</p> <pre>vsip_vgetlength_f vsip_vgetlength_d vsip_vgetlength_i vsip_vgetlength_si vsip_cvgetlength_f vsip_cvgetlength_d vsip_cvgetlength_i vsip_cvgetlength_si vsip_vgetlength_bl vsip_vgetlength_vi vsip_vgetlength_mi</pre>
<pre>vsip_offset vsip_Dvgetoffset_P(const vsip_Dvview_P * vector);</pre>	<p>Get the offset attribute of a vector view object. The following instances are supported:</p> <pre>vsip_vgetoffset_f vsip_vgetoffset_d vsip_vgetoffset_i vsip_vgetoffset_si vsip_cvgetoffset_f vsip_cvgetoffset_d vsip_cvgetoffset_i vsip_cvgetoffset_si vsip_vgetoffset_bl vsip_vgetoffset_vi vsip_vgetoffset_mi</pre>
<pre>vsip_stride vsip_Dvgetstride_P(const vsip_Dvview_P * vector);</pre>	<p>Get the stride attribute of a vector view object. The following instances are supported:</p> <pre>vsip_vgetstride_f vsip_vgetstride_d vsip_vgetstride_i vsip_vgetstride_si vsip_cvgetstride_f vsip_cvgetstride_d vsip_cvgetstride_i vsip_cvgetstride_si vsip_vgetstride_bl vsip_vgetstride_vi vsip_vgetstride_mi</pre>
<pre>vsip_vview_P * vsip_vimagview_P(const vsip_cvview_P * complex_vector);</pre>	<p>Create a vector view object of the imaginary part of a complex vector from a complex vector view object. The following instances are supported:</p> <pre>vsip_vimagview_f vsip_vimagview_d vsip_vimagview_i vsip_vimagview_si</pre>

Prototype	Description
<pre>void vsip_Dvput_P(vsip_Dvview_P * vector, vsip_index j, vsip_Dscalar_P value);</pre>	<p>Set the value of a specified element of a vector view object. The following instances are supported:</p> <pre>vsip_vput_f vsip_vput_d vsip_vput_i vsip_vput_si vsip_cvput_f vsip_cvput_d vsip_cvput_i vsip_cvput_si vsip_vput_bl vsip_vput_vi vsip_vput_mi</pre>
<pre>vsip_Dvview_P * vsip_Dvputattrib_P(vsip_Dvview_P * vector, const vsip_Dvattr_P * attr);</pre>	<p>Set the attributes of a vector view object. The following instances are supported:</p> <pre>vsip_vputattrib_f vsip_vputattrib_d vsip_vputattrib_i vsip_vputattrib_si vsip_cvputattrib_f vsip_cvputattrib_d vsip_cvputattrib_i vsip_cvputattrib_si vsip_vputattrib_bl vsip_vputattrib_vi vsip_vputattrib_mi</pre>
<pre>vsip_Dvview_P * vsip_Dvputlength_P(vsip_Dvview_P * vector, vsip_length length);</pre>	<p>Set the length attribute of a vector view object. The following instances are supported:</p> <pre>vsip_vputlength_f vsip_vputlength_d vsip_vputlength_i vsip_vputlength_si vsip_cvputlength_f vsip_cvputlength_d vsip_cvputlength_i vsip_cvputlength_si vsip_vputlength_bl vsip_vputlength_vi vsip_vputlength_mi</pre>
<pre>vsip_Dvview_P * vsip_Dvputoffset_P(vsip_Dvview_P * vector, vsip_offset offset);</pre>	<p>Set the offset attribute of a vector view object. The following instances are supported:</p> <pre>vsip_vputoffset_f vsip_vputoffset_d vsip_vputoffset_i vsip_vputoffset_si vsip_cvputoffset_f vsip_cvputoffset_d vsip_cvputoffset_i vsip_cvputoffset_si vsip_vputoffset_bl vsip_vputoffset_vi vsip_vputoffset_mi</pre>

Prototype	Description
<pre>vsip_Dvview_P * vsip_Dvputstride_P(vsip_Dvview_P * vector, vsip_stride stride);</pre>	<p>Set the stride attribute of a vector view object. The following instances are supported:</p> <pre>vsip_vputstride_f vsip_vputstride_d vsip_vputstride_i vsip_vputstride_si vsip_cvputstride_f vsip_cvputstride_d vsip_cvputstride_i vsip_cvputstride_si vsip_vputstride_bl vsip_vputstride_vi vsip_vputstride_mi</pre>
<pre>vsip_vview_P * vsip_vrealview_P(const vsip_cvview_P * complex_vector);</pre>	<p>Create a vector view object of the real part of a complex vector from a complex vector view object. The following instances are supported:</p> <pre>vsip_vrealview_f vsip_vrealview_d vsip_vrealview_i vsip_vrealview_si</pre>
<pre>vsip_Dvview_P * vsip_Dvsubview_P(const vsip_Dvview_P * vector, vsip_index j, vsip_length n);</pre>	<p>Create a vector view object that is a subview of a vector view object. The following instances are supported:</p> <pre>vsip_vsubview_f vsip_vsubview_d vsip_vsubview_i vsip_vsubview_si vsip_cvsubview_f vsip_cvsubview_d vsip_cvsubview_i vsip_cvsubview_si vsip_vsubview_bl vsip_vsubview_vi vsip_vsubview_mi</pre>

1.4 Matrix View Functions

Prototype	Description
<pre>void vsip_Dmalldestroy_P(vsip_Dmview_P * matrix);</pre>	<p>Destroy a matrix, its associated block, and any VSIPL data array bound to the block. The following instances are supported:</p> <pre>vsip_malldestroy_f vsip_malldestroy_d vsip_malldestroy_i vsip_malldestroy_si vsip_cmalldestroy_f vsip_cmalldestroy_d vsip_cmalldestroy_i vsip_cmalldestroy_si vsip_malldestroy_bl</pre>

Prototype	Description
<pre>vsip_Dmview_P * vsip_Dmbind_P(vsip_Dblock_P * block, vsip_offset offset, vsip_stride col_stride, vsip_length col_length, vsip_stride row_stride, vsip_length row_length);</pre>	<p>Create a matrix view object and bind it to a block object. The following instances are supported:</p> <pre>vsip_mbind_f vsip_mbind_d vsip_mbind_i vsip_mbind_si vsip_cmbind_f vsip_cmbind_d vsip_cmbind_i vsip_cmbind_si vsip_mbind_bl</pre>
<pre>vsip_Dmview_P * vsip_Dmcloneview_P(const vsip_Dmview_P * matrix);</pre>	<p>Create a clone of a matrix view. The following instances are supported:</p> <pre>vsip_mcloneview_f vsip_mcloneview_d vsip_mcloneview_i vsip_mcloneview_si vsip_cmcloneview_f vsip_cmcloneview_d vsip_cmcloneview_i vsip_cmcloneview_si vsip_mcloneview_bl</pre>
<pre>vsip_Dvview_P * vsip_Dmcolview_P(const vsip_Dmview_P * matrix, vsip_index j);</pre>	<p>Create a vector view object of a specified column of the source matrix view object. The following instances are supported:</p> <pre>vsip_mcolview_f vsip_mcolview_d vsip_mcolview_i vsip_mcolview_si vsip_cmcolview_f vsip_cmcolview_d vsip_cmcolview_i vsip_cmcolview_si vsip_mcolview_bl</pre>
<pre>vsip_Dmview_P * vsip_Dmcreate_P(vsip_length col_length, vsip_length row_length, vsip_major rc, vsip_memory_hint hint);</pre>	<p>Creates a block object and matrix view object of the block. The following instances are supported:</p> <pre>vsip_mcreate_f vsip_mcreate_d vsip_mcreate_i vsip_mcreate_si vsip_cmcreate_f vsip_cmcreate_d vsip_cmcreate_i vsip_cmcreate_si vsip_mcreate_bl</pre>

Prototype	Description
<pre>vsip_Dblock_P * vsip_Dmdestroy_P(vsip_Dmview_P * matrix);</pre>	<p>Destroy a matrix view object and returns a pointer to the associated block object.</p> <p>The following instances are supported:</p> <pre>vsip_mdestroy_f vsip_mdestroy_d vsip_mdestroy_i vsip_mdestroy_si vsip_cmdestroy_f vsip_cmdestroy_d vsip_cmdestroy_i vsip_cmdestroy_si vsip_mdestroy_bl</pre>
<pre>vsip_Dvview_P * vsip_Dmdiagview_P(const vsip_Dmview_P * matrix, vsip_stride index);</pre>	<p>Create a vector view object of a matrix diagonal of a matrix view object.</p> <p>The following instances are supported:</p> <pre>vsip_mdiagview_f vsip_mdiagview_d vsip_mdiagview_i vsip_mdiagview_si vsip_cmdiagview_f vsip_cmdiagview_d vsip_cmdiagview_i vsip_cmdiagview_si vsip_mdiagview_bl</pre>
<pre>vsip_Dscalar_P vsip_Dmget_P(const vsip_Dmview_P * matrix, vsip_index i, vsip_index j);</pre>	<p>Get the value of a specified element of a matrix view object.</p> <p>The following instances are supported:</p> <pre>vsip_mget_f vsip_mget_d vsip_mget_i vsip_mget_si vsip_cmget_f vsip_cmget_d vsip_cmget_i vsip_cmget_si vsip_mget_bl</pre>
<pre>void vsip_Dmgetattrib_P(const vsip_Dmview_P * matrix, vsip_Dmattr_P * attr);</pre>	<p>Get the attributes of a matrix view object.</p> <p>The following instances are supported:</p> <pre>vsip_mgetattrib_f vsip_mgetattrib_d vsip_mgetattrib_i vsip_mgetattrib_si vsip_cmgetattrib_f vsip_cmgetattrib_d vsip_cmgetattrib_i vsip_cmgetattrib_si vsip_mgetattrib_bl</pre>

Prototype	Description
<pre>vsip_Dblock_P * vsip_Dmgetblock_P(const vsip_Dmview_P * matrix);</pre>	<p>Get the block attribute of a matrix view object. The following instances are supported:</p> <pre>vsip_mgetblock_f vsip_mgetblock_d vsip_mgetblock_i vsip_mgetblock_si vsip_cmgetblock_f vsip_cmgetblock_d vsip_cmgetblock_i vsip_cmgetblock_si vsip_mgetblock_bl</pre>
<pre>vsip_length vsip_Dmgetcollength_P(const vsip_Dmview_P * matrix);</pre>	<p>Get the column length attribute of a matrix view object. The following instances are supported:</p> <pre>vsip_mgetcollength_f vsip_mgetcollength_d vsip_mgetcollength_i vsip_mgetcollength_si vsip_cmgetcollength_f vsip_cmgetcollength_d vsip_cmgetcollength_i vsip_cmgetcollength_si vsip_mgetcollength_bl</pre>
<pre>vsip_stride vsip_Dmgetcolstride_P(const vsip_Dmview_P * matrix);</pre>	<p>Get the column stride attribute of a matrix view object. The following instances are supported:</p> <pre>vsip_mgetcolstride_f vsip_mgetcolstride_d vsip_mgetcolstride_i vsip_mgetcolstride_si vsip_cmgetcolstride_f vsip_cmgetcolstride_d vsip_cmgetcolstride_i vsip_cmgetcolstride_si vsip_mgetcolstride_bl</pre>
<pre>vsip_offset vsip_Dmgetoffset_P(const vsip_Dmview_P * matrix);</pre>	<p>Get the offset attribute of a matrix view object. The following instances are supported:</p> <pre>vsip_mgetoffset_f vsip_mgetoffset_d vsip_mgetoffset_i vsip_mgetoffset_si vsip_cmgetoffset_f vsip_cmgetoffset_d vsip_cmgetoffset_i vsip_cmgetoffset_si vsip_mgetoffset_bl</pre>

Prototype	Description
<pre>vsip_length vsip_Dmgetrowlength_P(const vsip_Dmview_P * matrix);</pre>	<p>Get the row length attribute of a matrix view object. The following instances are supported:</p> <pre>vsip_mgetrowlength_f vsip_mgetrowlength_d vsip_cmgetrowlength_f vsip_cmgetrowlength_d vsip_cmgetrowlength_i vsip_cmgetrowlength_si</pre>
<pre>vsip_stride vsip_Dmgetrowstride_P(const vsip_Dmview_P * matrix);</pre>	<p>Get the row stride attribute of a matrix view object. The following instances are supported:</p> <pre>vsip_mgetrowstride_f vsip_mgetrowstride_d vsip_mgetrowstride_i vsip_mgetrowstride_si vsip_cmgetrowstride_f vsip_cmgetrowstride_d vsip_cmgetrowstride_i vsip_cmgetrowstride_si vsip_mgetrowstride_bl</pre>
<pre>vsip_mview_P * vsip_mimagview_P(const vsip_cmview_P * complex_matrix);</pre>	<p>Create a matrix view object of the imaginary part of complex matrix from a complex matrix view object. The following instances are supported:</p> <pre>vsip_mimagview_f vsip_mimagview_d vsip_mimagview_i vsip_mimagview_si</pre>
<pre>void vsip_Dmput_P(const vsip_Dmview_P * matrix, vsip_index i, vsip_index j, vsip_Dscalar_P value);</pre>	<p>Set the value of a specified element of a matrix view object. The following instances are supported:</p> <pre>vsip_mput_f vsip_mput_d vsip_mput_i vsip_mput_si vsip_cmput_f vsip_cmput_d vsip_cmput_i vsip_cmput_si vsip_mput_bl</pre>
<pre>vsip_Dmview_P * vsip_Dmputattrib_P(vsip_Dmview_P * matrix, const vsip_Dmattrib_P * attr);</pre>	<p>Set the attributes of a matrix view object. The following instances are supported:</p> <pre>vsip_mputattrib_f vsip_mputattrib_d vsip_mputattrib_i vsip_mputattrib_si vsip_cmputattrib_f vsip_cmputattrib_d vsip_cmputattrib_i vsip_cmputattrib_si vsip_mputattrib_bl</pre>

Prototype	Description
<pre>vsip_Dmview_P * vsip_Dmputcollength_P(vsip_Dmview_P * matrix, vsip_length n2);</pre>	<p>Set the column length attribute of a matrix view object. The following instances are supported:</p> <pre>vsip_mputcollength_f vsip_mputcollength_d vsip_mputcollength_i vsip_mputcollength_si vsip_cputcollength_f vsip_cputcollength_d vsip_cputcollength_i vsip_cputcollength_si vsip_mputcollength_bl</pre>
<pre>vsip_Dmview_P * vsip_Dmputcolstride_P(vsip_Dmview_P * matrix, vsip_stride s2);</pre>	<p>Set the column stride attribute of a matrix view object. The following instances are supported:</p> <pre>vsip_mputcolstride_f vsip_mputcolstride_d vsip_mputcolstride_i vsip_mputcolstride_si vsip_cputcolstride_f vsip_cputcolstride_d vsip_cputcolstride_i vsip_cputcolstride_si vsip_mputcolstride_bl</pre>
<pre>vsip_Dmview_P * vsip_Dmputoffset_P(vsip_Dmview_P * matrix, vsip_offset offset);</pre>	<p>Set the offset attribute of a matrix view object. The following instances are supported:</p> <pre>vsip_mputoffset_f vsip_mputoffset_d vsip_mputoffset_i vsip_mputoffset_si vsip_cputoffset_f vsip_cputoffset_d vsip_cputoffset_i vsip_cputoffset_si vsip_mputoffset_bl</pre>
<pre>vsip_Dmview_P * vsip_Dmputrowlength_P(vsip_Dmview_P * matrix, vsip_length n1);</pre>	<p>Set the row length attribute of a matrix view object. The following instances are supported:</p> <pre>vsip_mputrowlength_f vsip_mputrowlength_d vsip_mputrowlength_i vsip_mputrowlength_si vsip_cputrowlength_f vsip_cputrowlength_d vsip_cputrowlength_i vsip_cputrowlength_si vsip_mputrowlength_bl</pre>

Prototype	Description
<pre>vsip_Dmview_P * vsip_Dmputrowstride_P(vsip_Dmview_P * matrix, vsip_stride s1);</pre>	<p>Set the row stride attribute of a matrix view object.</p> <p>The following instances are supported:</p> <pre>vsip_mputrowstride_f vsip_mputrowstride_d vsip_mputrowstride_i vsip_mputrowstride_si vsip_cmputrowstride_f vsip_cmputrowstride_d vsip_cmputrowstride_i vsip_cmputrowstride_si vsip_mputrowstride_bl</pre>
<pre>vsip_mview_P * vsip_mrealview_P(const vsip_cmview_P * complex_matrix);</pre>	<p>Create a matrix view object of the real part of complex matrix from a complex matrix view object.</p> <p>The following instances are supported:</p> <pre>vsip_mrealview_f vsip_mrealview_d vsip_mrealview_i vsip_mrealview_si</pre>
<pre>vsip_Dvview_P * vsip_Dmrowview_P(const vsip_Dmview_P * matrix, vsip_index i);</pre>	<p>Create a vector view object of a specified row of the source matrix view object.</p> <p>The following instances are supported:</p> <pre>vsip_mrowview_f vsip_mrowview_d vsip_mrowview_i vsip_mrowview_si vsip_cmrowview_f vsip_cmrowview_d vsip_cmrowview_i vsip_cmrowview_si vsip_mrowview_bl</pre>
<pre>vsip_Dmview_P * vsip_Dmsubview_P(const vsip_Dmview_P * matrix, vsip_index i, vsip_index j, vsip_length m, vsip_length n);</pre>	<p>Create a matrix view object that is a subview of matrix view object.</p> <p>The following instances are supported:</p> <pre>vsip_msubview_f vsip_msubview_d vsip_msubview_i vsip_msubview_si vsip_cmsubview_f vsip_cmsubview_d vsip_cmsubview_i vsip_cmsubview_si vsip_msubview_bl</pre>

Prototype	Description
<pre>vsip_Dmview_P * vsip_Dmtransview_P(const vsip_Dmview_P * matrix);</pre>	<p>Create a matrix view object that is the transpose of a matrix view object. The following instances are supported:</p> <pre>vsip_mtransview_f vsip_mtransview_d vsip_mtransview_i vsip_mtransview_si vsip_cmtransview_f vsip_cmtransview_d vsip_cmtransview_i vsip_cmtransview_si vsip_mtransview_bl</pre>

Chapter 2. Scalar Functions

2.1 Real Scalar Functions

Prototype	Description
<pre>vsip_scalar_P vsip_acos_P(const vsip_scalar_P A);</pre>	Computes the principal radian value in $[0, \pi]$ of the inverse cosine of a scalar. The following instances are supported: <code>vsip_acos_f</code> <code>vsip_acos_d</code>
<pre>vsip_scalar_P vsip_asin_P(const vsip_scalar_P A);</pre>	Computes the principal radian value in $[0, \pi]$ of the inverse sine of a scalar. The following instances are supported: <code>vsip_asin_f</code> <code>vsip_asin_d</code>
<pre>vsip_scalar_P vsip_atan_P(const vsip_scalar_P A);</pre>	Computes the principal radian value in $[-\pi/2, \pi/2]$ of the inverse tangent of a scalar. The following instances are supported: <code>vsip_atan_f</code> <code>vsip_atan_d</code>
<pre>vsip_scalar_P vsip_atan2_P(const vsip_scalar_P A, const vsip_scalar_P B);</pre>	Computes the four-quadrant radian value in $[-\pi, \pi]$ of the inverse tangent of the ratio of two scalars. The following instances are supported: <code>vsip_atan2_f</code> <code>vsip_atan2_d</code>
<pre>vsip_scalar_P vsip_ceil_P(const vsip_scalar_P A);</pre>	Computes the ceiling of a scalar. The following instances are supported: <code>vsip_ceil_f</code> <code>vsip_ceil_d</code>
<pre>vsip_scalar_P vsip_cos_P(const vsip_scalar_P A);</pre>	Computes the cosine of a scalar angle in radians. The following instances are supported: <code>vsip_cos_f</code> <code>vsip_cos_d</code>
<pre>vsip_scalar_P vsip_cosh_P(const vsip_scalar_P A);</pre>	Computes the hyperbolic cosine of a scalar. The following instances are supported: <code>vsip_cosh_f</code> <code>vsip_cosh_d</code>
<pre>vsip_scalar_P vsip_exp_P(const vsip_scalar_P A);</pre>	Computes the exponential of a scalar. The following instances are supported: <code>vsip_exp_f</code> <code>vsip_exp_d</code>

Prototype	Description
<pre>vsip_scalar_P vsip_floor_P(const vsip_scalar_P A);</pre>	<p>Computes the floor of a scalar. The following instances are supported:</p> <pre>vsip_floor_f vsip_floor_d</pre>
<pre>vsip_scalar_P vsip_log_P(const vsip_scalar_P A);</pre>	<p>Computes the natural logarithm of a scalar. The following instances are supported:</p> <pre>vsip_log_f vsip_log_d</pre>
<pre>vsip_scalar_P vsip_log10_P(const vsip_scalar_P A);</pre>	<p>Computes the base 10 logarithm of a scalar. The following instances are supported:</p> <pre>vsip_log10_f vsip_log10_d</pre>
<pre>vsip_scalar_P vsip_mag_P(const vsip_scalar_P A);</pre>	<p>Computes the magnitude (absolute value) of a scalar. The following instances are supported:</p> <pre>vsip_mag_f vsip_mag_d</pre>
<pre>vsip_scalar_P vsip_pow_P(const vsip_scalar_P A, const vsip_scalar_P B);</pre>	<p>Computes the power function of two scalars. The following instances are supported:</p> <pre>vsip_pow_f vsip_pow_d</pre>
<pre>vsip_scalar_P vsip_sin_P(const vsip_scalar_P A);</pre>	<p>Computes the sine of a scalar angle in radians. The following instances are supported:</p> <pre>vsip_sin_f vsip_sin_d</pre>
<pre>vsip_scalar_P vsip_sinh_P(const vsip_scalar_P A);</pre>	<p>Computes the hyperbolic sine of a scalar. The following instances are supported:</p> <pre>vsip_sinh_f vsip_sinh_d</pre>
<pre>vsip_scalar_P vsip_sqrt_P(const vsip_scalar_P A);</pre>	<p>Computes the square root of a scalar. The following instances are supported:</p> <pre>vsip_sqrt_f vsip_sqrt_d</pre>
<pre>vsip_scalar_P vsip_tan_P(const vsip_scalar_P A);</pre>	<p>Computes the tangent of a scalar angle in radians. The following instances are supported:</p> <pre>vsip_tan_f vsip_tan_d</pre>

Prototype	Description
<pre>vsip_scalar_P vsip_tanh_P(const vsip_scalar_P A);</pre>	<p>Computes the hyperbolic tangent of a scalar.</p> <p>The following instances are supported:</p> <pre>vsip_tanh_f vsip_tanh_d</pre>

2.2 Complex Scalar Functions

Prototype	Description
<pre>vsip_scalar_P vsip_arg_P(vsip_cscalar_P x);</pre>	<p>Returns the argument in radians $[-\pi, \pi]$ of a complex scalar.</p> <p>The following instances are supported:</p> <pre>vsip_arg_f vsip_arg_d</pre>
<pre>void vsip_CADD_P(vsip_cscalar_P x, vsip_cscalar_P y, vsip_cscalar_P * z);</pre>	<p>Computes the complex sum of two scalars.</p> <p>The following instances are supported:</p> <pre>vsip_CADD_f vsip_CADD_d</pre>
<pre>vsip_cscalar_P vsip_cadd_P(vsip_cscalar_P x, vsip_cscalar_P y);</pre>	<p>Computes the complex sum of two scalars.</p> <p>The following instances are supported:</p> <pre>vsip_cadd_f vsip_cadd_d</pre>
<pre>void vsip_RCADD_P(vsip_scalar_P x, vsip_cscalar_P y, vsip_cscalar_P * z);</pre>	<p>Computes the complex sum of two scalars.</p> <p>The following instances are supported:</p> <pre>vsip_RCADD_f vsip_RCADD_d</pre>
<pre>vsip_cscalar_P vsip_rcadd_P(vsip_scalar_P x, vsip_cscalar_P y);</pre>	<p>Computes the complex sum of two scalars.</p> <p>The following instances are supported:</p> <pre>vsip_rcadd_f vsip_rcadd_d</pre>
<pre>void vsip_CDIV_P(vsip_cscalar_P x, vsip_cscalar_P y, vsip_cscalar_P * z);</pre>	<p>Computes the complex quotient of two scalars.</p> <p>The following instances are supported:</p> <pre>vsip_CDIV_f vsip_CDIV_d</pre>
<pre>vsip_cscalar_P vsip_cdiv_P(vsip_cscalar_P x, vsip_cscalar_P y);</pre>	<p>Computes the complex quotient of two scalars.</p> <p>The following instances are supported:</p> <pre>vsip_cdiv_f vsip_cdiv_d</pre>

Prototype	Description
<pre>void vsip_CRDIV_P(vsip_cscalar_P x, vsip_scalar_P y, vsip_cscalar_P * z);</pre>	<p>Computes the complex quotient of two scalars. The following instances are supported:</p> <p><code>vsip_CRDIV_f</code> <code>vsip_CRDIV_d</code></p>
<pre>vsip_cscalar_P vsip_crdiv_P(vsip_cscalar_P x, vsip_scalar_P y);</pre>	<p>Computes the complex quotient of two scalars. The following instances are supported:</p> <p><code>vsip_crdiv_f</code> <code>vsip_crdiv_d</code></p>
<pre>void vsip_CEXP_P(vsip_cscalar_P x, vsip_cscalar_P * y);</pre>	<p>Computes the exponential of a scalar. The following instances are supported:</p> <p><code>vsip_CEXP_f</code> <code>vsip_CEXP_d</code></p>
<pre>vsip_cscalar_P vsip_cexp_P(vsip_cscalar_P x);</pre>	<p>Computes the complex exponential of a scalar. The following instances are supported:</p> <p><code>vsip_cexp_f</code> <code>vsip_cexp_d</code></p>
<pre>void vsip_CJMUL_P(vsip_cscalar_P x, vsip_cscalar_P y, vsip_cscalar_P * z);</pre>	<p>Computes the product a complex scalar with the conjugate of a second complex scalar. The following instances are supported:</p> <p><code>vsip_CJMUL_f</code> <code>vsip_CJMUL_d</code></p>
<pre>vsip_cscalar_P vsip_cjmul_P(vsip_cscalar_P x, vsip_cscalar_P y);</pre>	<p>Computes the product a complex scalar with the conjugate of a second complex scalar. The following instances are supported:</p> <p><code>vsip_cjmul_f</code> <code>vsip_cjmul_d</code></p>
<pre>vsip_scalar_P vsip_cmag_P(vsip_cscalar_P x);</pre>	<p>Computes the magnitude of a complex scalar. The following instances are supported:</p> <p><code>vsip_cmag_f</code> <code>vsip_cmag_d</code></p>
<pre>vsip_scalar_P vsip_cmagsq_P(vsip_cscalar_P x);</pre>	<p>Computes the magnitude squared of a complex scalar. The following instances are supported:</p> <p><code>vsip_cmagsq_f</code> <code>vsip_cmagsq_d</code></p>
<pre>void vsip_CMPLX_P(vsip_scalar_P a, vsip_scalar_P b, vsip_cscalar_P * r);</pre>	<p>Form a complex scalar from two real scalars. The following instances are supported:</p> <p><code>vsip_CMPLX_f</code> <code>vsip_CMPLX_d</code></p>

Prototype	Description
<pre>vsip_cscalar_P vsip_cmplx_P(vsip_scalar_P re, vsip_scalar_P im);</pre>	<p>Form a complex scalar from two real scalars. The following instances are supported:</p> <p><code>vsip_cmplx_f</code> <code>vsip_cmplx_d</code></p>
<pre>void vsip_CMUL_P(vsip_cscalar_P x, vsip_cscalar_P y, vsip_cscalar_P * z);</pre>	<p>Computes the complex product of two scalars. The following instances are supported:</p> <p><code>vsip_CMUL_f</code> <code>vsip_CMUL_d</code></p>
<pre>vsip_cscalar_P vsip_cmul_P(vsip_cscalar_P x, vsip_cscalar_P y);</pre>	<p>Computes the complex product of two scalars. The following instances are supported:</p> <p><code>vsip_cmul_f</code> <code>vsip_cmul_d</code></p>
<pre>void vsip_RCMUL_P(vsip_scalar_P x, vsip_cscalar_P y, vsip_cscalar_P * z);</pre>	<p>Computes the complex product of two scalars. The following instances are supported:</p> <p><code>vsip_RCMUL_f</code> <code>vsip_RCMUL_d</code></p>
<pre>vsip_cscalar_P vsip_rcmul_P(vsip_scalar_P x, vsip_cscalar_P y);</pre>	<p>Computes the complex product of two scalars. The following instances are supported:</p> <p><code>vsip_rcmul_f</code> <code>vsip_rcmul_d</code></p>
<pre>void vsip_CNEG_P(vsip_cscalar_P x, vsip_cscalar_P * y);</pre>	<p>Computes the negation of a complex scalar. The following instances are supported:</p> <p><code>vsip_CNEG_f</code> <code>vsip_CNEG_d</code></p>
<pre>vsip_cscalar_P vsip_cneg_P(vsip_cscalar_P x);</pre>	<p>Computes the negation of a complex scalar. The following instances are supported:</p> <p><code>vsip_cneg_f</code> <code>vsip_cneg_d</code></p>
<pre>void vsip_CONJ_P(vsip_cscalar_P x, vsip_cscalar_P * y);</pre>	<p>Computes the complex conjugate of a scalar. The following instances are supported:</p> <p><code>vsip_CONJ_f</code> <code>vsip_CONJ_d</code></p>
<pre>vsip_cscalar_P vsip_conj_P(vsip_cscalar_P x);</pre>	<p>Computes the complex conjugate of a scalar. The following instances are supported:</p> <p><code>vsip_conj_f</code> <code>vsip_conj_d</code></p>

Prototype	Description
<pre>void vsip_CRECIP_P(vsip_cscalar_P x, vsip_cscalar_P * y);</pre>	<p>Computes the reciprocal of a complex scalar. The following instances are supported:</p> <p><code>vsip_CRECIP_f</code> <code>vsip_CRECIP_d</code></p>
<pre>vsip_cscalar_P vsip_crecip_P(vsip_cscalar_P x);</pre>	<p>Computes the reciprocal of a complex scalar. The following instances are supported:</p> <p><code>vsip_crecip_f</code> <code>vsip_crecip_d</code></p>
<pre>void vsip_CSQRT_P(vsip_cscalar_P x, vsip_cscalar_P * y);</pre>	<p>Computes the square root a complex scalar. The following instances are supported:</p> <p><code>vsip_CSQRT_f</code> <code>vsip_CSQRT_d</code></p>
<pre>vsip_cscalar_P vsip_csqrt_P(vsip_cscalar_P x);</pre>	<p>Computes the square root a complex scalar. The following instances are supported:</p> <p><code>vsip_csqrt_f</code> <code>vsip_csqrt_d</code></p>
<pre>void vsip_CSUB_P(vsip_cscalar_P x, vsip_cscalar_P y, vsip_cscalar_P * z);</pre>	<p>Computes the complex difference of two scalars. The following instances are supported:</p> <p><code>vsip_CSUB_f</code> <code>vsip_CSUB_d</code></p>
<pre>vsip_cscalar_P vsip_csub_P(vsip_cscalar_P x, vsip_cscalar_P y);</pre>	<p>Computes the complex difference of two scalars. The following instances are supported:</p> <p><code>vsip_csub_f</code> <code>vsip_csub_d</code></p>
<pre>void vsip_RCSUB_P(vsip_scalar_P x, vsip_cscalar_P y, vsip_cscalar_P * z);</pre>	<p>Computes the complex difference of two scalars. The following instances are supported:</p> <p><code>vsip_RCSUB_f</code> <code>vsip_RCSUB_d</code></p>
<pre>vsip_cscalar_P vsip_rsub_P(vsip_scalar_P x, vsip_cscalar_P y);</pre>	<p>Computes the complex difference of two scalars. The following instances are supported:</p> <p><code>vsip_rsub_f</code> <code>vsip_rsub_d</code></p>
<pre>void vsip_CRSUB_P(vsip_cscalar_P x, vsip_scalar_P y, vsip_cscalar_P * z);</pre>	<p>Computes the complex difference of two scalars. The following instances are supported:</p> <p><code>vsip_CRSUB_f</code> <code>vsip_CRSUB_d</code></p>

Prototype	Description
<pre>vsip_cscalar_P vsip_crsub_P(vsip_cscalar_P x, vsip_scalar_P y);</pre>	<p>Computes the complex difference of two scalars. The following instances are supported:</p> <p><code>vsip_crsub_f</code> <code>vsip_crsub_d</code></p>
<pre>vsip_scalar_P vsip_imag_P(vsip_cscalar_P x);</pre>	<p>Extract the imaginary part of a complex scalar. The following instances are supported:</p> <p><code>vsip_imag_f</code> <code>vsip_imag_d</code></p>
<pre>void vsip_polar_P(vsip_cscalar_P a, vsip_scalar_P * r, vsip_scalar_P * t);</pre>	<p>Convert a complex scalar from rectangular to polar form. The polar data consists of a real scalar containing the radius and a corresponding real scalar containing the argument (angle) of the complex scalar. The following instances are supported:</p> <p><code>vsip_polar_f</code> <code>vsip_polar_d</code></p>
<pre>vsip_scalar_P vsip_real_P(vsip_cscalar_P x);</pre>	<p>Extract the real part of a complex scalar. The following instances are supported:</p> <p><code>vsip_real_f</code> <code>vsip_real_d</code></p>
<pre>void vsip_RECT_P(vsip_scalar_P radius, vsip_scalar_P theta, vsip_cscalar_P * r);</pre>	<p>Convert a pair of real scalars from complex polar to complex rectangular form. The following instances are supported:</p> <p><code>vsip_RECT_f</code> <code>vsip_RECT_d</code></p>
<pre>vsip_cscalar_P vsip_rect_P(vsip_scalar_P r, vsip_scalar_P t);</pre>	<p>Convert a pair of real scalars from complex polar to complex rectangular form. The following instances are supported:</p> <p><code>vsip_rect_f</code> <code>vsip_rect_d</code></p>

2.3 Index Scalar Functions

Prototype	Description
<pre>void vsip_MATINDEX(vsip_index r, vsip_index c, vsip_scalar_mi * mi);</pre>	Form a matrix index from two vector indices.
<pre>vsip_scalar_mi vsip_matindex(vsip_index r, vsip_index c);</pre>	Form a matrix index from two vector indices.
<pre>vsip_index vsip_mcolindex(vsip_scalar_mi mi);</pre>	Returns the column vector index from a matrix index.
<pre>vsip_index vsip_mrowindex(vsip_scalar_mi mi);</pre>	Returns the row vector index from a matrix index.

Chapter 3. Random Number Generation

3.1 Random Number Functions

Prototype	Description
<pre>vsip_randstate * vsip_randcreate(const vsip_index seed, const vsip_index numprocs, const vsip_index id, const vsip_rng portable);</pre>	Create a random number generator state object.
<pre>int vsip_randdestroy(vsip_randstate * rand);</pre>	Destroys (frees the memory used by) a random number generator state object. Returns zero on success, non-zero on failure.
<pre>vsip_scalar_P vsip_randu_P(vsip_randstate * state);</pre>	Generate a uniformly distributed (pseudo-)random number. Floating point values are uniformly distributed over the open interval (0,1). Integer deviates are uniformly distributed over the open interval $(0, 2^{31} - 1)$. The following instances are supported: vsip_randu_f vsip_randu_d
<pre>vsip_cscalar_P vsip_crandu_P(vsip_randstate * state);</pre>	Generate a uniformly distributed (pseudo-)random number. Floating point values are uniformly distributed over the open interval (0,1). Integer deviates are uniformly distributed over the open interval $(0, 2^{31} - 1)$. The following instances are supported: vsip_crandu_f vsip_crandu_d
<pre>void vsip_vrandu_P(vsip_randstate * state, const vsip_vview_P * R);</pre>	Generate a uniformly distributed (pseudo-)random number. Floating point values are uniformly distributed over the open interval (0,1). Integer deviates are uniformly distributed over the open interval $(0, 2^{31} - 1)$. The following instances are supported: vsip_vrandu_f vsip_vrandu_d

Prototype	Description
<pre>void vsip_cvrandu_P(vsip_randstate * state, const vsip_cvview_P * R);</pre>	<p>Generate a uniformly distributed (pseudo-)random number. Floating point values are uniformly distributed over the open interval (0,1). Integer deviates are uniformly distributed over the open interval $(0, 2^{31} - 1)$. The following instances are supported:</p> <p>vsip_cvrandu_f vsip_cvrandu_d</p>
<pre>vsip_scalar_P vsip_randn_P(vsip_randstate * state);</pre>	<p>Generate an approximately normally distributed (pseudo-)random deviate having mean zero and unit variance: $N(0, 1)$. The random numbers are generated by summing values returned by the uniform random number generator. The following instances are supported:</p> <p>vsip_randn_f vsip_randn_d</p>
<pre>vsip_cscalar_P vsip_crandn_P(vsip_randstate * state);</pre>	<p>Generate an approximately normally distributed (pseudo-)random deviate having mean zero and unit variance: $N(0, 1)$. The random numbers are generated by summing values returned by the uniform random number generator. The following instances are supported:</p> <p>vsip_crandn_f vsip_crandn_d</p>
<pre>vsip_scalar_P vsip_vrandn_P(vsip_randstate * state);</pre>	<p>Generate an approximately normally distributed (pseudo-)random deviate having mean zero and unit variance: $N(0, 1)$. The random numbers are generated by summing values returned by the uniform random number generator. The following instances are supported:</p> <p>vsip_vrandn_f vsip_vrandn_d</p>
<pre>void vsip_cvrandn_P(vsip_randstate * state, const vsip_cvview_P * R);</pre>	<p>Generate an approximately normally distributed (pseudo-)random deviate having mean zero and unit variance: $N(0, 1)$. The random numbers are generated by summing values returned by the uniform random number generator. The following instances are supported:</p> <p>vsip_cvrandn_f vsip_cvrandn_d</p>

Chapter 4. Elementwise Functions

4.1 Elementary Mathematical Functions

Prototype	Description
<pre>void vsip_vacos_P(const vsip_vview_P * A, const vsip_vview_P * R);</pre>	<p>Computes the principal radian value in $[0, \pi]$ of the inverse cosine for each element of a vector.</p> <p>The following instances are supported:</p> <p><code>vsip_vacos_f</code> <code>vsip_vacos_d</code></p>
<pre>void vsip_macos_P(const vsip_mview_P * A, const vsip_mview_P * R);</pre>	<p>Computes the principal radian value in $[0, \pi]$ of the inverse cosine for each element of a matrix.</p> <p>The following instances are supported:</p> <p><code>vsip_macos_f</code> <code>vsip_macos_d</code></p>
<pre>void vsip_vasin_P(const vsip_vview_P * A, const vsip_vview_P * R);</pre>	<p>Computes the principal radian value in $[0, \pi]$ of the inverse sine for each element of a vector.</p> <p>The following instances are supported:</p> <p><code>vsip_vasin_f</code> <code>vsip_vasin_d</code></p>
<pre>void vsip_masin_P(const vsip_mview_P * A, const vsip_mview_P * R);</pre>	<p>Computes the principal radian value in $[0, \pi]$ of the inverse sine for each element of a matrix.</p> <p>The following instances are supported:</p> <p><code>vsip_masin_f</code> <code>vsip_masin_d</code></p>
<pre>void vsip_vatan_P(const vsip_vview_P * A, const vsip_vview_P * R);</pre>	<p>Computes the principal radian value in $[-\pi/2, \pi/2]$ of the inverse tangent for each element of a vector.</p> <p>The following instances are supported:</p> <p><code>vsip_vatan_f</code> <code>vsip_vatan_d</code></p>
<pre>void vsip_matan_P(const vsip_mview_P * A, const vsip_mview_P * R);</pre>	<p>Computes the principal radian value in $[-\pi/2, \pi/2]$ of the inverse tangent for each element of a matrix.</p> <p>The following instances are supported:</p> <p><code>vsip_matan_f</code> <code>vsip_matan_d</code></p>

Prototype	Description
<pre>void vsip_vatan2_P(const vsip_vview_P * A, const vsip_vview_P * B, const vsip_vview_P * R);</pre>	<p>Computes the four-quadrant radian value in $[-\pi, \pi]$ of the inverse tangent of the ratio of the elements of two input vectors.</p> <p>The following instances are supported:</p> <p>vsip_vatan2_f vsip_vatan2_d</p>
<pre>void vsip_matan2_P(const vsip_mview_P * A, const vsip_mview_P * B, const vsip_mview_P * R);</pre>	<p>Computes the four-quadrant radian value in $[-\pi, \pi]$ of the inverse tangent of the ratio of the elements of two input matrices.</p> <p>The following instances are supported:</p> <p>vsip_matan2_f vsip_matan2_d</p>
<pre>void vsip_vcos_P(const vsip_vview_P * A, const vsip_vview_P * R);</pre>	<p>Computes the cosine for each element of a vector. Element angle values are in radians.</p> <p>The following instances are supported:</p> <p>vsip_vcos_f vsip_vcos_d</p>
<pre>void vsip_mcos_P(const vsip_mview_P * A, const vsip_mview_P * R);</pre>	<p>Computes the cosine for each element of a matrix. Element angle values are in radians.</p> <p>The following instances are supported:</p> <p>vsip_mcos_f vsip_mcos_d</p>
<pre>void vsip_vcosh_P(const vsip_vview_P * A, const vsip_vview_P * R);</pre>	<p>Computes the hyperbolic cosine for each element of a vector.</p> <p>The following instances are supported:</p> <p>vsip_vcosh_f vsip_vcosh_d</p>
<pre>void vsip_mcosh_P(const vsip_mview_P * A, const vsip_mview_P * R);</pre>	<p>Computes the hyperbolic cosine for each element of a matrix.</p> <p>The following instances are supported:</p> <p>vsip_mcosh_f vsip_mcosh_d</p>
<pre>void vsip_vexp_P(const vsip_vview_P * A, const vsip_vview_P * R);</pre>	<p>Computes the exponential function value for each element of a vector.</p> <p>The following instances are supported:</p> <p>vsip_vexp_f vsip_vexp_d</p>
<pre>void vsip_cvexp_P(const vsip_cvview_P * A, const vsip_cvview_P * R);</pre>	<p>Computes the exponential function value for each element of a vector.</p> <p>The following instances are supported:</p> <p>vsip_cvexp_f vsip_cvexp_d</p>

Prototype	Description
<pre>void vsip_mexp_P(const vsip_mview_P * A, const vsip_mview_P * R);</pre>	<p>Computes the exponential function value for each element of a matrix. The following instances are supported:</p> <p><code>vsip_mexp_f</code> <code>vsip_mexp_d</code></p>
<pre>void vsip_cmexp_P(const vsip_cmview_P * A, const vsip_cmview_P * R);</pre>	<p>Computes the exponential function value for each element of a matrix. The following instances are supported:</p> <p><code>vsip_cmexp_f</code> <code>vsip_cmexp_d</code></p>
<pre>void vsip_vexp10_P(const vsip_vview_P * A, const vsip_vview_P * R);</pre>	<p>Computes the base 10 exponential for each element of a vector. The following instances are supported:</p> <p><code>vsip_vexp10_f</code> <code>vsip_vexp10_d</code></p>
<pre>void vsip_mexp10_P(const vsip_mview_P * A, const vsip_mview_P * R);</pre>	<p>Computes the base 10 exponential for each element of a matrix. The following instances are supported:</p> <p><code>vsip_mexp10_f</code> <code>vsip_mexp10_d</code></p>
<pre>void vsip_vlog_P(const vsip_vview_P * A, const vsip_vview_P * R);</pre>	<p>Computes the natural logarithm for each element of a vector. The following instances are supported:</p> <p><code>vsip_vlog_f</code> <code>vsip_vlog_d</code></p>
<pre>void vsip_cvlog_P(const vsip_cvview_P * A, const vsip_cvview_P * R);</pre>	<p>Computes the natural logarithm for each element of a vector. The following instances are supported:</p> <p><code>vsip_cvlog_f</code> <code>vsip_cvlog_d</code></p>
<pre>void vsip_mlog_P(const vsip_mview_P * A, const vsip_mview_P * R);</pre>	<p>Computes the natural logarithm for each element of a matrix. The following instances are supported:</p> <p><code>vsip_mlog_f</code> <code>vsip_mlog_d</code></p>
<pre>void vsip_cmlog_P(const vsip_cmview_P * A, const vsip_cmview_P * R);</pre>	<p>Computes the natural logarithm for each element of a matrix. The following instances are supported:</p> <p><code>vsip_cmlog_f</code> <code>vsip_cmlog_d</code></p>
<pre>void vsip_vlog10_P(const vsip_vview_P * A, const vsip_vview_P * R);</pre>	<p>Compute the base ten logarithm for each element of a vector. The following instances are supported:</p> <p><code>vsip_vlog10_f</code> <code>vsip_vlog10_d</code></p>

Prototype	Description
<pre>void vsip_mlog10_P(const vsip_mview_P * A, const vsip_mview_P * R);</pre>	<p>Compute the base ten logarithm for each element of a matrix.</p> <p>The following instances are supported:</p> <p>vsip_mlog10_f vsip_mlog10_d</p>
<pre>void vsip_vsin_P(const vsip_vview_P * A, const vsip_vview_P * R);</pre>	<p>Compute the sine for each element of a vector. Element angle values are in radians.</p> <p>The following instances are supported:</p> <p>vsip_vsin_f vsip_vsin_d</p>
<pre>void vsip_msin_P(const vsip_mview_P * A, const vsip_mview_P * R);</pre>	<p>Compute the sine for each element of a matrix. Element angle values are in radians.</p> <p>The following instances are supported:</p> <p>vsip_msin_f vsip_msin_d</p>
<pre>void vsip_vsinh_P(const vsip_vview_P * A, const vsip_vview_P * R);</pre>	<p>Computes the hyperbolic sine for each element of a vector.</p> <p>The following instances are supported:</p> <p>vsip_vsinh_f vsip_vsinh_d</p>
<pre>void vsip_msinh_P(const vsip_mview_P * A, const vsip_mview_P * R);</pre>	<p>Computes the hyperbolic sine for each element of a matrix.</p> <p>The following instances are supported:</p> <p>vsip_msinh_f vsip_msinh_d</p>
<pre>void vsip_Dvsqrt_P(const vsip_Dvview_P * A, const vsip_Dvview_P * R);</pre>	<p>Compute the square root for each element of a vector.</p> <p>The following instances are supported:</p> <p>vsip_vsqrt_f vsip_vsqrt_d vsip_cvsqrt_f vsip_cvsqrt_d</p>
<pre>void vsip_Dmsqrt_P(const vsip_Dmview_P * A, const vsip_Dmview_P * R);</pre>	<p>Compute the square root for each element of a matrix.</p> <p>The following instances are supported:</p> <p>vsip_msqrt_f vsip_msqrt_d vsip_cmsqrt_f vsip_cmsqrt_d</p>
<pre>void vsip_vtan_P(const vsip_vview_P * A, const vsip_vview_P * R);</pre>	<p>Compute the tangent for each element of a vector. Element angle values are in radians.</p> <p>The following instances are supported:</p> <p>vsip_vtan_f vsip_vtan_d</p>

Prototype	Description
<pre>void vsip_mtanh_P(const vsip_mview_P * A, const vsip_mview_P * R);</pre>	<p>Compute the tangent for each element of a matrix. Element angle values are in radians.</p> <p>The following instances are supported:</p> <p><code>vsip_mtanh_f</code> <code>vsip_mtanh_d</code></p>
<pre>void vsip_vtanh_P(const vsip_vview_P * A, const vsip_vview_P * R);</pre>	<p>Computes the hyperbolic tangent for each element of a vector.</p> <p>The following instances are supported:</p> <p><code>vsip_vtanh_f</code> <code>vsip_vtanh_d</code></p>
<pre>void vsip_mtanh_P(const vsip_mview_P * A, const vsip_mview_P * R);</pre>	<p>Computes the hyperbolic tangent for each element of a matrix.</p> <p>The following instances are supported:</p> <p><code>vsip_mtanh_f</code> <code>vsip_mtanh_d</code></p>

4.2 Unary Operations

Prototype	Description
<pre>void vsip_varg_P(const vsip_cvview_P * A, const vsip_vview_P * R);</pre>	<p>Computes the argument in radians $[-\pi, \pi]$ for each element of a complex vector.</p> <p>The following instances are supported:</p> <p><code>vsip_varg_f</code> <code>vsip_varg_d</code></p>
<pre>void vsip_marg_P(const vsip_cmview_P * A, const vsip_mview_P * R);</pre>	<p>Computes the argument in radians $[-\pi, \pi]$ for each element of a complex matrix.</p> <p>The following instances are supported:</p> <p><code>vsip_marg_f</code> <code>vsip_marg_d</code></p>
<pre>void vsip_vceil_P(const vsip_vview_P * A, const vsip_vview_P * R);</pre>	<p>Computes the ceiling for each element of a vector.</p> <p>The following instances are supported:</p> <p><code>vsip_vceil_f</code> <code>vsip_vceil_d</code></p>
<pre>void vsip_cvconj_P(const vsip_cvview_P * A, const vsip_cvview_P * R);</pre>	<p>Compute the conjugate for each element of a complex vector.</p> <p>The following instances are supported:</p> <p><code>vsip_cvconj_f</code> <code>vsip_cvconj_d</code></p>
<pre>void vsip_cmconj_P(const vsip_cmview_P * A, const vsip_cmview_P * R);</pre>	<p>Compute the conjugate for each element of a complex matrix.</p> <p>The following instances are supported:</p> <p><code>vsip_cmconj_f</code> <code>vsip_cmconj_d</code></p>

Prototype	Description
<pre>void vsip_Dvcumsum_P(const vsip_Dvview_P * A, const vsip_Dvview_P * R);</pre>	<p>Compute the cumulative sum of the elements of a vector. The following instances are supported:</p> <pre>vsip_vcumsum_f vsip_vcumsum_d vsip_vcumsum_i vsip_cvcumsum_f vsip_cvcumsum_d vsip_cvcumsum_i</pre>
<pre>void vsip_Dmcumsum_P(vsip_major dir, const vsip_Dmview_P * R);</pre>	<p>Compute the cumulative sums of the elements in the rows or columns of a matrix. The following instances are supported:</p> <pre>vsip_mcumsum_f vsip_mcumsum_d vsip_mcumsum_i vsip_cmcumsum_f vsip_cmcumsum_d vsip_cmcumsum_i</pre>
<pre>void vsip_veuler_P(const vsip_vview_P * A, const vsip_cvview_P * R);</pre>	<p>Computes the complex numbers corresponding to the angle of a unit vector in the complex plane for each element of a vector. The following instances are supported:</p> <pre>vsip_veuler_f vsip_veuler_d</pre>
<pre>void vsip_meuler_P(const vsip_mview_P * A, const vsip_cmview_P * R);</pre>	<p>Computes the complex numbers corresponding to the angle of a unit vector in the complex plane for each element of a matrix. The following instances are supported:</p> <pre>vsip_meuler_f vsip_meuler_d</pre>
<pre>void vsip_vfloor_P(const vsip_vview_P * A, const vsip_vview_P * R);</pre>	<p>Computes the floor for each element of a vector. The following instances are supported:</p> <pre>vsip_vfloor_f vsip_vfloor_d</pre>
<pre>void vsip_Dvmag_P(const vsip_Dvview_P * A, const vsip_vview_P * R);</pre>	<p>Compute the magnitude for each element of a vector. The following instances are supported:</p> <pre>vsip_vmag_f vsip_vmag_d vsip_vmag_i vsip_vmag_si vsip_cvmag_f vsip_cvmag_d</pre>

Prototype	Description
<pre>void vsip_Dmmag_P(const vsip_Dmview_P * A, const vsip_mview_P * R);</pre>	<p>Compute the magnitude for each element of a matrix. The following instances are supported:</p> <pre>vsip_mmag_f vsip_mmag_d vsip_cmmag_f vsip_cmmag_d</pre>
<pre>void vsip_vcmagsq_P(const vsip_cvview_P * A, const vsip_vview_P * R);</pre>	<p>Computes the square of the magnitudes for each element of a vector. The following instances are supported:</p> <pre>vsip_vcmagsq_f vsip_vcmagsq_d</pre>
<pre>void vsip_mcmagsq_P(const vsip_cmview_P * A, const vsip_mview_P * R);</pre>	<p>Computes the square of the magnitudes for each element of a matrix. The following instances are supported:</p> <pre>vsip_mcmagsq_f vsip_mcmagsq_d</pre>
<pre>vsip_Dscalar_P vsip_Dvmeanval_P(const vsip_Dvview_P * A);</pre>	<p>Returns the mean value of the elements of a vector. The following instances are supported:</p> <pre>vsip_vmeanval_f vsip_vmeanval_d vsip_cvmeanval_f vsip_cvmeanval_d</pre>
<pre>vsip_Dscalar_P vsip_Dmmeanval_P(const vsip_Dmview_P * A);</pre>	<p>Returns the mean value of the elements of a matrix. The following instances are supported:</p> <pre>vsip_mmeanval_f vsip_mmeanval_d vsip_cmmeanval_f vsip_cmmeanval_d</pre>
<pre>vsip_scalar_P vsip_Dvmeansqval_P(const vsip_Dvview_P * A);</pre>	<p>Returns the mean magnitude squared value of the elements of a vector. The following instances are supported:</p> <pre>vsip_vmeansqval_f vsip_vmeansqval_d vsip_cvmeansqval_f vsip_cvmeansqval_d</pre>
<pre>vsip_scalar_P vsip_Dmmeansqval_P(const vsip_Dmview_P * A);</pre>	<p>Returns the mean magnitude squared value of the elements of a matrix. The following instances are supported:</p> <pre>vsip_mmeansqval_f vsip_mmeansqval_d vsip_cmmeansqval_f vsip_cmmeansqval_d</pre>

Prototype	Description
<pre>vsip_scalar_P vsip_Dvmodulate_P(const vsip_Dvview_P * A, const vsip_scalar_P nu, const vsip_scalar_P phi, const vsip_Dvview_P * R);</pre>	<p>Computes the modulation of a real vector by a specified complex frequency. The following instances are supported:</p> <pre>vsip_vmodulate_f vsip_vmodulate_d vsip_cvmodulate_f vsip_cvmodulate_d</pre>
<pre>void vsip_Dvneg_P(const vsip_Dvview_P * A, const vsip_Dvview_P * R);</pre>	<p>Computes the negation for each element of a vector. The following instances are supported:</p> <pre>vsip_vneg_f vsip_vneg_d vsip_vneg_i vsip_vneg_si vsip_cvneg_f vsip_cvneg_d</pre>
<pre>void vsip_Dmneg_P(const vsip_Dmview_P * A, const vsip_Dmview_P * R);</pre>	<p>Computes the negation for each element of a matrix. The following instances are supported:</p> <pre>vsip_mneg_f vsip_mneg_d vsip_mneg_i vsip_cmneg_f vsip_cmneg_d</pre>
<pre>void vsip_Dvrecip_P(const vsip_Dvview_P * A, const vsip_Dvview_P * R);</pre>	<p>Computes the reciprocal for each element of a vector. The following instances are supported:</p> <pre>vsip_vrecip_f vsip_vrecip_d vsip_cvrecip_f vsip_cvrecip_d</pre>
<pre>void vsip_Dmrecip_P(const vsip_Dmview_P * A, const vsip_Dmview_P * R);</pre>	<p>Computes the reciprocal for each element of a matrix. The following instances are supported:</p> <pre>vsip_mrecip_f vsip_mrecip_d vsip_cmrecip_f vsip_cmrecip_d</pre>
<pre>void vsip_Dvrsqrt_P(const vsip_Dvview_P * A, const vsip_Dvview_P * R);</pre>	<p>Computes the reciprocal of the square root for each element of a vector. The following instances are supported:</p> <pre>vsip_vrsqrt_f vsip_vrsqrt_d</pre>
<pre>void vsip_Dmrsqrt_P(const vsip_Dmview_P * A, const vsip_Dmview_P * R);</pre>	<p>Computes the reciprocal of the square root for each element of a matrix. The following instances are supported:</p> <pre>vsip_mrsqrt_f vsip_mrsqrt_d</pre>

Prototype	Description
<pre>void vsip_Dvsq_P(const vsip_Dvview_P * A, const vsip_Dvview_P * R);</pre>	<p>Computes the square for each element of a vector. The following instances are supported:</p> <pre>vsip_vsq_f vsip_vsq_d</pre>
<pre>void vsip_Dmsq_P(const vsip_Dmview_P * A, const vsip_Dmview_P * R);</pre>	<p>Computes the square for each element of a matrix. The following instances are supported:</p> <pre>vsip_msq_f vsip_msq_d</pre>
<pre>vsip_scalar_P vsip_Dvsumval_P(const vsip_vview_P * A);</pre>	<p>Returns the sum of the elements of a vector. The following instances are supported:</p> <pre>vsip_vsumval_f vsip_vsumval_d vsip_vsumval_i vsip_vsumval_si vsip_vsumval_bl vsip_cvsumval_f vsip_cvsumval_d vsip_cvsumval_i</pre>
<pre>vsip_scalar_P vsip_Dmsumval_P(const vsip_mview_P * A);</pre>	<p>Returns the sum of the elements of a vector. The following instances are supported:</p> <pre>vsip_msumval_f vsip_msumval_d vsip_msumval_i vsip_cmsumval_f vsip_cmsumval_d vsip_cmsumval_i</pre>
<pre>vsip_Dscalar_P vsip_Dvsumsqval_P(const vsip_Dvview_P * A);</pre>	<p>Returns the sum of the squares of the elements of a vector. The following instances are supported:</p> <pre>vsip_vsumsqval_f vsip_vsumsqval_d</pre>
<pre>vsip_Dscalar_P vsip_Dmsumsqval_P(const vsip_Dmview_P * A);</pre>	<p>Returns the sum of the squares of the elements of a matrix. The following instances are supported:</p> <pre>vsip_msumsqval_f vsip_msumsqval_d</pre>

4.3 Binary Operations

Prototype	Description
<pre>void vsip_Dvadd_P(const vsip_Dvview_P * A, const vsip_Dvview_P * B, const vsip_Dvview_P * R);</pre>	<p>Computes the sum, by element, of two vectors. The following instances are supported:</p> <pre>vsip_vadd_f vsip_vadd_d vsip_vadd_i vsip_vadd_si vsip_cvadd_f vsip_cvadd_d vsip_cvadd_i</pre>
<pre>void vsip_Dmadd_P(const vsip_Dmview_P * A, const vsip_Dmview_P * B, const vsip_Dmview_P * R);</pre>	<p>Computes the sum, by element, of two matrices. The following instances are supported:</p> <pre>vsip_madd_f vsip_madd_d vsip_madd_i vsip_cmadd_f vsip_cmadd_d</pre>
<pre>void vsip_rcvadd_P(const vsip_vview_P * A, const vsip_cvview_P * B, const vsip_cvview_P * R);</pre>	<p>Computes the sum, by element, of two vectors. The following instances are supported:</p> <pre>vsip_rcvadd_f vsip_rcvadd_d</pre>
<pre>void vsip_rcmadd_P(const vsip_mview_P * A, const vsip_cmview_P * B, const vsip_cmview_P * R);</pre>	<p>Computes the sum, by element, of two matrices. The following instances are supported:</p> <pre>vsip_rcmadd_f vsip_rcmadd_d</pre>
<pre>void vsip_Dsvadd_P(const vsip_Dscalar_P a, const vsip_Dvview_P * B, const vsip_Dvview_P * R);</pre>	<p>Computes the sum, by element, of a scalar and a vector. The following instances are supported:</p> <pre>vsip_svadd_f vsip_svadd_d vsip_svadd_i vsip_svadd_si vsip_csvadd_f vsip_csvadd_d</pre>
<pre>void vsip_Dsmadd_P(const vsip_Dscalar_P a, const vsip_Dmview_P * B, const vsip_Dmview_P * R);</pre>	<p>Computes the sum, by element, of a scalar and a matrix. The following instances are supported:</p> <pre>vsip_smadd_f vsip_smadd_d vsip_smadd_i vsip_csmadd_f vsip_csmadd_d</pre>
<pre>void vsip_rscvadd_P(const vsip_scalar_P a, const vsip_cvview_P * B, const vsip_cvview_P * R);</pre>	<p>Computes the sum, by element, of a real scalar and a complex vector. The following instances are supported:</p> <pre>vsip_rscvadd_f vsip_rscvadd_d</pre>

Prototype	Description
<pre>void vsip_rscmadd_P(const vsip_scalar_P a, const vsip_cmview_P * B, const vsip_cmview_P * R);</pre>	<p>Computes the sum, by element, of a real scalar and a complex matrix. The following instances are supported:</p> <p><code>vsip_rscmadd_f</code> <code>vsip_rscmadd_d</code></p>
<pre>void vsip_Dvdiv_P(const vsip_Dvview_P * A, const vsip_Dvview_P * B, const vsip_Dvview_P * R);</pre>	<p>Computes the quotient, by element, of two vectors. The following instances are supported:</p> <p><code>vsip_vdiv_f</code> <code>vsip_vdiv_d</code> <code>vsip_cvdiv_f</code> <code>vsip_cvdiv_d</code></p>
<pre>void vsip_Dmdiv_P(const vsip_Dmview_P * A, const vsip_Dmview_P * B, const vsip_Dmview_P * R);</pre>	<p>Computes the quotient, by element, of two matrices. The following instances are supported:</p> <p><code>vsip_mdiv_f</code> <code>vsip_mdiv_d</code> <code>vsip_cmdiv_f</code> <code>vsip_cmdiv_d</code></p>
<pre>void vsip_rcvdiv_P(const vsip_scalar_P a, const vsip_cvview_P * B, const vsip_cvview_P * R);</pre>	<p>Computes the quotient, by element, of two vectors. The following instances are supported:</p> <p><code>vsip_rcvdiv_f</code> <code>vsip_rcvdiv_d</code></p>
<pre>void vsip_rcmdiv_P(const vsip_scalar_P a, const vsip_cmview_P * B, const vsip_cmview_P * R);</pre>	<p>Computes the quotient, by element, of two matrices. The following instances are supported:</p> <p><code>vsip_rcmdiv_f</code> <code>vsip_rcmdiv_d</code></p>
<pre>void vsip_crvdiv_P(const vsip_cvview_P * A, const vsip_vview_P * B, const vsip_cvview_P * R);</pre>	<p>Computes the quotient, by element, of two vectors. The following instances are supported:</p> <p><code>vsip_crvdiv_f</code> <code>vsip_crvdiv_d</code></p>
<pre>void vsip_crmdiv_P(const vsip_cmview_P * A, const vsip_mview_P * B, const vsip_cmview_P * R);</pre>	<p>Computes the quotient, by element, of two matrices. The following instances are supported:</p> <p><code>vsip_crmdiv_f</code> <code>vsip_crmdiv_d</code></p>
<pre>void vsip_Dsvdiv_P(const vsip_Dscalar_P a, const vsip_Dvview_P * B, const vsip_Dvview_P * R);</pre>	<p>Computes the quotient, by element, of a scalar and a vector. The following instances are supported:</p> <p><code>vsip_svdiv_f</code> <code>vsip_svdiv_d</code></p>

Prototype	Description
<pre>void vsip_Dsmdiv_P(const vsip_Dscalar_P a, const vsip_Dmview_P * B, const vsip_Dmview_P * R);</pre>	<p>Computes the quotient, by element, of a scalar and a matrix. The following instances are supported:</p> <p><code>vsip_smdiv_f</code> <code>vsip_smdiv_d</code> <code>vsip_csmdiv_f</code> <code>vsip_csmdiv_d</code></p>
<pre>void vsip_rscvdiv_P(const vsip_scalar_P a, const vsip_cvview_P * B, const vsip_cvview_P * R);</pre>	<p>Computes the quotient, by element, of a real scalar and a complex vector. The following instances are supported:</p> <p><code>vsip_rscvdiv_f</code> <code>vsip_rscvdiv_d</code></p>
<pre>void vsip_rscvsub_P(const vsip_scalar_P a, const vsip_cvview_P * B, const vsip_cvview_P * R);</pre>	<p>Computes the difference, by element, of a real scalar and a complex vector. The following instances are supported:</p> <p><code>vsip_rscvsub_f</code> <code>vsip_rscvsub_d</code></p>
<pre>void vsip_rscmdiv_P(const vsip_scalar_P a, const vsip_cmview_P * B, const vsip_cmview_P * R);</pre>	<p>Computes the quotient, by element, of a real scalar and a complex matrix. The following instances are supported:</p> <p><code>vsip_rscmdiv_f</code> <code>vsip_rscmdiv_d</code></p>
<pre>void vsip_rscmsub_P(const vsip_scalar_P a, const vsip_cmview_P * B, const vsip_cmview_P * R);</pre>	<p>Computes the difference, by element, of a real scalar and a complex matrix. The following instances are supported:</p> <p><code>vsip_rscmsub_f</code> <code>vsip_rscmsub_d</code></p>
<pre>void vsip_Dvsdiv_P(const vsip_Dvview_P * A, const vsip_Dscalar_P b, const vsip_Dvview_P * R);</pre>	<p>Computes the quotient, by element, of a vector and a scalar. The following instances are supported:</p> <p><code>vsip_vsdiv_f</code> <code>vsip_vsdiv_d</code> <code>vsip_cvrsdiv_f</code> <code>vsip_cvrsdiv_d</code></p>
<pre>void vsip_Dmsdiv_P(const vsip_Dmview_P * A, const vsip_Dscalar_P b, const vsip_Dmview_P * R);</pre>	<p>Computes the quotient, by element, of a matrix and a scalar. The following instances are supported:</p> <p><code>vsip_msdiv_f</code> <code>vsip_msdiv_d</code> <code>vsip_cmrsdiv_f</code> <code>vsip_cmrsdiv_d</code></p>
<pre>void vsip_Dvexpoavg_P(const vsip_scalar_P a, const vsip_Dvview_P * B, const vsip_Dvview_P * C);</pre>	<p>Computes an exponential weighted average, by element, of two vectors. The following instances are supported:</p> <p><code>vsip_vexpoavg_f</code> <code>vsip_vexpoavg_d</code> <code>vsip_cvexpoavg_f</code> <code>vsip_cvexpoavg_d</code></p>

Prototype	Description
<pre>void vsip_Dmexpoavg_P(const vsip_scalar_P a, const vsip_Dmview_P * B, const vsip_Dmview_P * C);</pre>	<p>Computes an exponential weighted average, by element, of two matrices. The following instances are supported:</p> <p><code>vsip_mexpoavg_f</code> <code>vsip_mexpoavg_d</code> <code>vsip_cmexpoavg_f</code> <code>vsip_cmexpoavg_d</code></p>
<pre>void vsip_vhypot_P(const vsip_vview_P * A, const vsip_vview_P * B, const vsip_vview_P * R);</pre>	<p>Computes the square root of the sum of squares, by element, of two input vectors. The following instances are supported:</p> <p><code>vsip_vhypot_f</code> <code>vsip_vhypot_d</code></p>
<pre>void vsip_mhypot_P(const vsip_mview_P * A, const vsip_mview_P * B, const vsip_mview_P * R);</pre>	<p>Computes the square root of the sum of squares, by element, of two input matrices. The following instances are supported:</p> <p><code>vsip_mhypot_f</code> <code>vsip_mhypot_d</code></p>
<pre>void vsip_cvjmul_P(const vsip_cvview_P * A, const vsip_cvview_P * B, const vsip_cvview_P * R);</pre>	<p>Computes the product of a complex vector with the conjugate of a second complex vector, by element. The following instances are supported:</p> <p><code>vsip_cvjmul_f</code> <code>vsip_cvjmul_d</code></p>
<pre>void vsip_cmjmul_P(const vsip_cmview_P * A, const vsip_cmview_P * B, const vsip_cmview_P * R);</pre>	<p>Computes the product of a complex matrix with the conjugate of a second complex matrix, by element. The following instances are supported:</p> <p><code>vsip_cmjmul_f</code> <code>vsip_cmjmul_d</code></p>
<pre>void vsip_Dvmul_P(const vsip_Dvview_P * A, const vsip_Dvview_P * B, const vsip_Dvview_P * R);</pre>	<p>Computes the product, by element, of two vectors. The following instances are supported:</p> <p><code>vsip_vmul_f</code> <code>vsip_vmul_d</code> <code>vsip_vmul_i</code> <code>vsip_vmul_si</code> <code>vsip_cvmul_f</code> <code>vsip_cvmul_d</code></p>
<pre>void vsip_Dmmul_P(const vsip_Dmview_P * A, const vsip_Dmview_P * B, const vsip_Dmview_P * R);</pre>	<p>Computes the product, by element, of two matrices. The following instances are supported:</p> <p><code>vsip_mmul_f</code> <code>vsip_mmul_d</code> <code>vsip_mmul_i</code> <code>vsip_cmmul_f</code> <code>vsip_cmmul_d</code></p>

Prototype	Description
<pre>void vsip_rcvmul_P(const vsip_vview_P * A, const vsip_cvview_P * B, const vsip_cvview_P * R);</pre>	<p>Computes the product, by element, of two vectors.</p> <p>The following instances are supported:</p> <p><code>vsip_rcvmul_f</code> <code>vsip_rcvmul_d</code></p>
<pre>void vsip_rcmmul_P(const vsip_mview_P * A, const vsip_cmview_P * B, const vsip_cmview_P * R);</pre>	<p>Computes the product, by element, of two matrices.</p> <p>The following instances are supported:</p> <p><code>vsip_rcmmul_f</code> <code>vsip_rcmmul_d</code></p>
<pre>void vsip_Dsvmul_P(const vsip_Dscalar_P a, const vsip_Dvview_P * B, const vsip_Dvview_P * R);</pre>	<p>Computes the product, by element, of a scalar and a vector.</p> <p>The following instances are supported:</p> <p><code>vsip_svmul_f</code> <code>vsip_svmul_d</code> <code>vsip_svmul_i</code> <code>vsip_svmul_si</code> <code>vsip_csvmul_f</code> <code>vsip_csvmul_d</code></p>
<pre>void vsip_Dsmmul_P(const vsip_Dscalar_P a, const vsip_Dmview_P * B, const vsip_Dmview_P * R);</pre>	<p>Computes the product, by element, of a scalar and a matrix.</p> <p>The following instances are supported:</p> <p><code>vsip_smmul_f</code> <code>vsip_smmul_d</code> <code>vsip_csmmul_f</code> <code>vsip_csmmul_d</code></p>
<pre>void vsip_rscvmul_P(const vsip_scalar_P a, const vsip_cvview_P * B, const vsip_cvview_P * R);</pre>	<p>Computes the product, by element, of a real scalar and a complex vector.</p> <p>The following instances are supported:</p> <p><code>vsip_rscvmul_f</code> <code>vsip_rscvmul_d</code></p>
<pre>void vsip_rscmmul_P(const vsip_scalar_P a, const vsip_cmview_P * B, const vsip_cmview_P * R);</pre>	<p>Computes the product, by element, of a real scalar and a complex matrix.</p> <p>The following instances are supported:</p> <p><code>vsip_rscmmul_f</code> <code>vsip_rscmmul_d</code></p>
<pre>void vsip_DvDmmul_P(const vsip_Dvview_P * A, const vsip_Dmview_P * B, const vsip_major major, const vsip_Dmview_P * R);</pre>	<p>Computes the product, by element, of a vector and the rows or columns of a matrix.</p> <p>The following instances are supported:</p> <p><code>vsip_vmmul_f</code> <code>vsip_vmmul_d</code> <code>vsip_cvmmul_f</code> <code>vsip_cvmmul_d</code></p>
<pre>void vsip_rvcmmul_P(const vsip_vview_P * A, const vsip_cmview_P * B, const vsip_major major, const vsip_cmview_P * R);</pre>	<p>Computes the product, by element, of a vector and the rows or columns of a matrix.</p> <p>The following instances are supported:</p> <p><code>vsip_rvcmmul_f</code> <code>vsip_rvcmmul_d</code></p>

Prototype	Description
<pre>void vsip_Dvsub_P(const vsip_Dvview_P * A, const vsip_Dvview_P * B, const vsip_Dvview_P * R);</pre>	<p>Computes the difference, by element, of two vectors.</p> <p>The following instances are supported:</p> <pre>vsip_vsub_f vsip_vsub_d vsip_vsub_i vsip_vsub_si vsip_cvsub_f vsip_cvsub_d</pre>
<pre>void vsip_Dmsub_P(const vsip_Dmview_P * A, const vsip_Dmview_P * B, const vsip_Dmview_P * R);</pre>	<p>Computes the difference, by element, of two matrices.</p> <p>The following instances are supported:</p> <pre>vsip_msub_f vsip_msub_d vsip_msub_i vsip_cmsub_f vsip_cmsub_d</pre>
<pre>void vsip_crsub_P(const vsip_cvview_P * A, const vsip_vview_P * B, const vsip_cvview_P * R);</pre>	<p>Computes the difference, by element, of two vectors.</p> <p>The following instances are supported:</p> <pre>vsip_crsub_f vsip_crsub_d</pre>
<pre>void vsip_crmsub_P(const vsip_cmview_P * A, const vsip_mview_P * B, const vsip_cmview_P * R);</pre>	<p>Computes the difference, by element, of two matrices.</p> <p>The following instances are supported:</p> <pre>vsip_crmsub_f vsip_crmsub_d</pre>
<pre>void vsip_rcvsub_P(const vsip_vview_P * A, const vsip_cvview_P * B, const vsip_cvview_P * R);</pre>	<p>Computes the difference, by element, of two vectors.</p> <p>The following instances are supported:</p> <pre>vsip_rcvsub_f vsip_rcvsub_d</pre>
<pre>void vsip_rcmsub_P(const vsip_mview_P * A, const vsip_cmview_P * B, const vsip_cmview_P * R);</pre>	<p>Computes the difference, by element, of two matrices.</p> <p>The following instances are supported:</p> <pre>vsip_rcmsub_f vsip_rcmsub_d</pre>
<pre>void vsip_Dsvsub_P(const vsip_Dscalar_P a, const vsip_Dvview_P * B, const vsip_Dvview_P * R);</pre>	<p>Computes the difference, by element, of a scalar and a vector.</p> <p>The following instances are supported:</p> <pre>vsip_svsub_f vsip_svsub_d vsip_svsub_i vsip_svsub_si vsip_csvsub_f vsip_csvsub_d</pre>

Prototype	Description
<pre>void vsip_Dsmsub_P(const vsip_Dscalar_P a, const vsip_Dmview_P * B, const vsip_Dmview_P * R);</pre>	<p>Computes the difference, by element, of a scalar and a matrix. The following instances are supported:</p> <pre>vsip_smsub_f vsip_smsub_d vsip_smsub_i vsip_csmsub_f vsip_csmsub_d</pre>

4.4 Ternary Operations

Prototype	Description
<pre>void vsip_Dvam_P(const vsip_Dvview_P * A, const vsip_Dvview_P * B, const vsip_Dvview_P * C, const vsip_Dvview_P * R);</pre>	<p>Computes the sum of two vectors and product of a third vector, by element. The following instances are supported:</p> <pre>vsip_vam_f vsip_vam_d vsip_cvam_f vsip_cvam_d</pre>
<pre>void vsip_Dvma_P(const vsip_Dvview_P * A, const vsip_Dvview_P * B, const vsip_Dvview_P * C, const vsip_Dvview_P * R);</pre>	<p>Computes the product of two vectors and sum of a third vector, by element. The following instances are supported:</p> <pre>vsip_vma_f vsip_vma_d vsip_cvma_f vsip_cvma_d</pre>
<pre>void vsip_Dvmsa_P(const vsip_Dvview_P * A, const vsip_Dvview_P * B, const vsip_Dscalar_P c, const vsip_Dvview_P * R);</pre>	<p>Computes the product of two vectors and sum of a scalar, by element. The following instances are supported:</p> <pre>vsip_vmsa_f vsip_vmsa_d vsip_cvmsa_f vsip_cvmsa_d</pre>
<pre>void vsip_Dvmsb_P(const vsip_Dvview_P * A, const vsip_Dvview_P * B, const vsip_Dvview_P * C, const vsip_Dvview_P * R);</pre>	<p>Computes the product of two vectors and difference of a third vector, by element. The following instances are supported:</p> <pre>vsip_vmsb_f vsip_vmsb_d vsip_cvmsb_f vsip_cvmsb_d</pre>
<pre>void vsip_Dvsam_P(const vsip_Dvview_P * A, const vsip_Dscalar_P b, const vsip_Dvview_P * C, const vsip_Dvview_P * R);</pre>	<p>Computes the sum of a vector and a scalar, and product with a second vector, by element. The following instances are supported:</p> <pre>vsip_vsam_f vsip_vsam_d vsip_cvsam_f vsip_cvsam_d</pre>

Prototype	Description
<pre>void vsip_Dvsbm_P(const vsip_Dvview_P * A, const vsip_Dvview_P * B, const vsip_Dvview_P * C, const vsip_Dvview_P * R);</pre>	<p>Computes the difference of two vectors, and product with a third vector, by element.</p> <p>The following instances are supported:</p> <pre>vsip_vsbm_f vsip_vsbm_d vsip_cvsbm_f vsip_cvsbm_d</pre>
<pre>void vsip_Dvsma_P(const vsip_Dvview_P * A, const vsip_Dscalar_P b, const vsip_Dvview_P * C, const vsip_Dvview_P * R);</pre>	<p>Computes the product of a vector and a scalar, and sum with a second vector, by element.</p> <p>The following instances are supported:</p> <pre>vsip_vsma_f vsip_vsma_d vsip_cvsm_a_f vsip_cvsm_a_d</pre>
<pre>void vsip_Dvsmsa_P(const vsip_Dvview_P * A, const vsip_Dscalar_P b, const vsip_Dscalar_P c, const vsip_Dvview_P * R);</pre>	<p>Computes the product of a vector and a scalar, and sum with a second scalar, by element.</p> <p>The following instances are supported:</p> <pre>vsip_vmsa_f vsip_vmsa_d vsip_cvmsa_f vsip_cvmsa_d</pre>

4.5 Logical Operations

Prototype	Description
<pre>vsip_scalar_bl vsip_valltrue_bl(const vsip_vview_bl * A);</pre>	Returns true if all the elements of a vector are true.
<pre>vsip_scalar_bl vsip_malltrue_bl(const vsip_vview_bl * A);</pre>	Returns true if all the elements of a vector are true.
<pre>vsip_scalar_bl vsip_vanytrue_bl(const vsip_vview_bl * A);</pre>	Returns true if one or more elements of a vector are true.
<pre>vsip_scalar_bl vsip_manytrue_bl(const vsip_vview_bl * A);</pre>	Returns true if one or more elements of a vector are true.
<pre>void vsip_Dvleq_P(const vsip_Dvview_P * A, const vsip_Dvview_P * B, const vsip_vview_bl * R);</pre>	<p>Computes the boolean comparison of 'equal', by element, of two vectors.</p> <p>The following instances are supported:</p> <pre>vsip_vleq_f vsip_vleq_d vsip_vleq_i vsip_cvleq_f vsip_cvleq_d vsip_cvleq_i</pre>

Prototype	Description
<pre>void vsip_Dmleq_P(const vsip_Dmview_P * A, const vsip_Dmview_P * B, const vsip_vview_bl * R);</pre>	<p>Computes the boolean comparison of 'equal', by element, of two vectors/matrices.</p> <p>The following instances are supported:</p> <pre>vsip_mleq_f vsip_mleq_d vsip_mleq_i vsip_cmleq_f vsip_cmleq_d vsip_cmleq_i</pre>
<pre>void vsip_vlge_P(const vsip_vview_P * A, const vsip_vview_P * B, const vsip_vview_bl * R);</pre>	<p>Computes the boolean comparison of 'greater than or equal', by element, of two vectors.</p> <p>The following instances are supported:</p> <pre>vsip_vlge_f vsip_vlge_d vsip_vlge_i</pre>
<pre>void vsip_mlge_P(const vsip_mview_P * A, const vsip_mview_P * B, const vsip_vview_bl * R);</pre>	<p>Computes the boolean comparison of 'greater than or equal', by element, of two vectors/matrices.</p> <p>The following instances are supported:</p> <pre>vsip_mlge_f vsip_mlge_d vsip_mlge_i</pre>
<pre>void vsip_vlgt_P(const vsip_vview_P * A, const vsip_vview_P * B, const vsip_vview_bl * R);</pre>	<p>Computes the boolean comparison of 'greater than', by element, of two vectors.</p> <p>The following instances are supported:</p> <pre>vsip_vlgt_f vsip_vlgt_d vsip_vlgt_i</pre>
<pre>void vsip_mlgt_P(const vsip_mview_P * A, const vsip_mview_P * B, const vsip_vview_bl * R);</pre>	<p>Computes the boolean comparison of 'greater than', by element, of two vectors/matrices.</p> <p>The following instances are supported:</p> <pre>vsip_mlgt_f vsip_mlgt_d vsip_mlgt_i</pre>
<pre>void vsip_vlle_P(const vsip_vview_P * A, const vsip_vview_P * B, const vsip_vview_bl * R);</pre>	<p>Computes the boolean comparison of 'less than or equal', by element, of two vectors.</p> <p>The following instances are supported:</p> <pre>vsip_vlle_f vsip_vlle_d vsip_vlle_i</pre>

Prototype	Description
<pre>void vsip_mlle_P(const vsip_mview_P * A, const vsip_mview_P * B, const vsip_vview_bl * R);</pre>	<p>Computes the boolean comparison of ‘less than or equal’, by element, of two vectors/matrices.</p> <p>The following instances are supported:</p> <pre>vsip_mlle_f vsip_mlle_d vsip_mlle_i</pre>
<pre>void vsip_vllt_P(const vsip_vview_P * A, const vsip_vview_P * B, const vsip_vview_bl * R);</pre>	<p>Computes the boolean comparison of ‘less than’, by element, of two vectors.</p> <p>The following instances are supported:</p> <pre>vsip_vllt_f vsip_vllt_d vsip_vllt_i</pre>
<pre>void vsip_mllt_P(const vsip_mview_P * A, const vsip_mview_P * B, const vsip_vview_bl * R);</pre>	<p>Computes the boolean comparison of ‘less than’, by element, of two vectors/matrices.</p> <p>The following instances are supported:</p> <pre>vsip_mllt_f vsip_mllt_d vsip_mllt_i</pre>
<pre>void vsip_Dvlne_P(const vsip_Dvview_P * A, const vsip_Dvview_P * B, const vsip_vview_bl * R);</pre>	<p>Computes the boolean comparison of ‘not equal’, by element, of two vectors.</p> <p>The following instances are supported:</p> <pre>vsip_vlne_f vsip_vlne_d vsip_vlne_i vsip_cvln_e_f vsip_cvln_e_d vsip_cvln_e_i</pre>
<pre>void vsip_Dmlne_P(const vsip_Dmview_P * A, const vsip_Dmview_P * B, const vsip_vview_bl * R);</pre>	<p>Computes the boolean comparison of ‘not equal’, by element, of two vectors/matrices.</p> <p>The following instances are supported:</p> <pre>vsip_mlne_f vsip_mlne_d vsip_mlne_i vsip_cmlne_f vsip_cmlne_d vsip_cmlne_i</pre>

4.6 Selection Operations

Prototype	Description
<pre>void vsip_vclip_P(const vsip_vview_P * A, const vsip_scalar_P t1, const vsip_scalar_P t2, const vsip_scalar_P c1, const vsip_scalar_P c2, const vsip_vview_P * R);</pre>	<p>Computes the generalised double clip, by element, of two vectors.</p> <p>The following instances are supported:</p> <pre>vsip_vclip_f vsip_vclip_d vsip_vclip_i vsip_vclip_si</pre>

Prototype	Description
<pre>void vsip_vinvclip_P(const vsip_vview_P * A, const vsip_scalar_P t1, const vsip_scalar_P t2, const vsip_scalar_P t3, const vsip_scalar_P c1, const vsip_scalar_P c2, const vsip_rview_P * R);</pre>	<p>Computes the generalised inverted double clip, by element, of two vectors. The following instances are supported:</p> <p><code>vsip_vinvclip_f</code> <code>vsip_vinvclip_d</code> <code>vsip_vinvclip_i</code> <code>vsip_vinvclip_si</code></p>
<pre>vsip_length vsip_vindexbool(const vsip_vview_bl * X, vsip_vview_vi * Y);</pre>	<p>Computes an index vector of the indices of the non-false elements of the boolean vector, and returns the number of non-false elements.</p>
<pre>void vsip_vmax_P(const vsip_vview_P * A, const vsip_vview_P * B, const vsip_rview_P * R);</pre>	<p>Computes the maximum, by element, of two vectors. The following instances are supported:</p> <p><code>vsip_vmax_f</code> <code>vsip_vmax_d</code></p>
<pre>void vsip_vmaxmg_P(const vsip_vview_P * A, const vsip_vview_P * B, const vsip_rview_P * R);</pre>	<p>Computes the maximum magnitude (absolute value), by element, of two vectors. The following instances are supported:</p> <p><code>vsip_vmaxmg_f</code> <code>vsip_vmaxmg_d</code></p>
<pre>void vsip_vcmaxmgsq_P(const vsip_cvview_P * A, const vsip_cvview_P * B, const vsip_rview_P * R);</pre>	<p>Computes the maximum magnitude squared, by element, of two complex vectors. The following instances are supported:</p> <p><code>vsip_vcmaxmgsq_f</code> <code>vsip_vcmaxmgsq_d</code></p>
<pre>vsip_scalar_P vsip_vcmaxmgsqval_P(const vsip_cvview_P * A, vsip_index * index);</pre>	<p>Returns the index and value of the maximum magnitude squared of the elements of a complex vector. The index is returned by reference as one of the arguments. The following instances are supported:</p> <p><code>vsip_vcmaxmgsqval_f</code> <code>vsip_vcmaxmgsqval_d</code></p>
<pre>vsip_scalar_P vsip_vmaxmgval_P(const vsip_vview_P * A, vsip_index * index);</pre>	<p>Returns the index and value of the maximum absolute value of the elements of a vector. The index is returned by reference as one of the arguments. The following instances are supported:</p> <p><code>vsip_vmaxmgval_f</code> <code>vsip_vmaxmgval_d</code></p>
<pre>vsip_scalar_P vsip_vmaxval_P(const vsip_vview_P * A, vsip_index * index);</pre>	<p>Returns the index and value of the maximum value of the elements of a vector. The index is returned by reference as one of the arguments. The following instances are supported:</p> <p><code>vsip_vmaxval_f</code> <code>vsip_vmaxval_d</code></p>

Prototype	Description
<pre>void vsip_vmin_P(const vsip_vview_P * A, const vsip_vview_P * B, const vsip_vview_P * R);</pre>	<p>Computes the minimum, by element, of two vectors.</p> <p>The following instances are supported:</p> <p><code>vsip_vmin_f</code> <code>vsip_vmin_d</code></p>
<pre>void vsip_vminmg_P(const vsip_vview_P * A, const vsip_vview_P * B, const vsip_vview_P * R);</pre>	<p>Computes the minimum magnitude (absolute value), by element, of two vectors.</p> <p>The following instances are supported:</p> <p><code>vsip_vminmg_f</code> <code>vsip_vminmg_d</code></p>
<pre>void vsip_vcminmgsq_P(const vsip_cvview_P * A, const vsip_cvview_P * B, const vsip_vview_P * R);</pre>	<p>Computes the minimum magnitude squared, by element, of two complex vectors.</p> <p>The following instances are supported:</p> <p><code>vsip_vcminmgsq_f</code> <code>vsip_vcminmgsq_d</code></p>
<pre>vsip_scalar_P vsip_vcminmgsqval_P(const vsip_cvview_P * A, vsip_index * index);</pre>	<p>Returns the index and value of the minimum magnitude squared of the elements of a complex vector. The index is returned by reference as one of the arguments.</p> <p>The following instances are supported:</p> <p><code>vsip_vcminmgsqval_f</code> <code>vsip_vcminmgsqval_d</code></p>
<pre>vsip_scalar_P vsip_vminmgval_P(const vsip_vview_P * A, vsip_index * index);</pre>	<p>Returns the index and value of the minimum absolute value of the elements of a vector. The index is returned by reference as one of the arguments.</p> <p>The following instances are supported:</p> <p><code>vsip_vminmgval_f</code> <code>vsip_vminmgval_d</code></p>
<pre>vsip_scalar_P vsip_vminval_P(const vsip_vview_P * A, vsip_index * index);</pre>	<p>Returns the index and value of the minimum value of the elements of a vector. The index is returned by reference as one of the arguments.</p> <p>The following instances are supported:</p> <p><code>vsip_vminval_f</code> <code>vsip_vminval_d</code></p>

4.7 Bitwise and Boolean Logical Operators

Prototype	Description
<pre>void vsip_vand_P(const vsip_vview_P * A, const vsip_vview_P * B, const vsip_vview_P * R);</pre>	<p>Computes the bitwise and, by element, of two vectors.</p> <p>The following instances are supported:</p> <p><code>vsip_vand_i</code> <code>vsip_vand_si</code> <code>vsip_vand_bl</code></p>

Prototype	Description
<pre>void vsip_mand_P(const vsip_mview_P * A, const vsip_mview_P * B, const vsip_mview_P * R);</pre>	<p>Computes the bitwise and, by element, of two matrices.</p> <p>The following instances are supported:</p> <pre>vsip_mand_i vsip_mand_si vsip_mand_bl</pre>
<pre>void vsip_vnot_P(const vsip_vview_P * A, const vsip_vview_P * R);</pre>	<p>Computes the bitwise not (one's complement), by element, of two vectors.</p> <p>The following instances are supported:</p> <pre>vsip_vnot_i vsip_vnot_si vsip_vnot_bl</pre>
<pre>void vsip_mnot_P(const vsip_mview_P * A, const vsip_mview_P * R);</pre>	<p>Computes the bitwise not (one's complement), by element, of two matrices.</p> <p>The following instances are supported:</p> <pre>vsip_mnot_i vsip_mnot_si vsip_mnot_bl</pre>
<pre>void vsip_vor_P(const vsip_vview_P * A, const vsip_vview_P * B, const vsip_vview_P * R);</pre>	<p>Computes the bitwise inclusive or, by element, of two vectors.</p> <p>The following instances are supported:</p> <pre>vsip_vor_i vsip_vor_si vsip_vor_bl</pre>
<pre>void vsip_mor_P(const vsip_mview_P * A, const vsip_mview_P * B, const vsip_mview_P * R);</pre>	<p>Computes the bitwise inclusive or, by element, of two matrices.</p> <p>The following instances are supported:</p> <pre>vsip_mor_i vsip_mor_si vsip_mor_bl</pre>
<pre>void vsip_vxor_P(const vsip_vview_P * A, const vsip_vview_P * B, const vsip_vview_P * R);</pre>	<p>Computes the bitwise exclusive or, by element, of two vectors.</p> <p>The following instances are supported:</p> <pre>vsip_vxor_i vsip_vxor_si vsip_vxor_bl</pre>
<pre>void vsip_mxor_P(const vsip_mview_P * A, const vsip_mview_P * B, const vsip_mview_P * R);</pre>	<p>Computes the bitwise exclusive or, by element, of two matrices.</p> <p>The following instances are supported:</p> <pre>vsip_mxor_i vsip_mxor_si vsip_mxor_bl</pre>

4.8 Element Generation and Copy

Prototype	Description
<pre>void vsip_Dvcopy_P_P(const vsip_Dvview_P * A, const vsip_Dvview_P * R);</pre>	<p>Copy the source vector to the destination vector performing any necessary type conversion of the standard ANSI C scalar types.</p> <p>The following instances are supported:</p> <pre>vsip_vcopy_f_f vsip_vcopy_f_d vsip_vcopy_d_f vsip_vcopy_d_d vsip_vcopy_f_i vsip_vcopy_d_i vsip_vcopy_f_si vsip_vcopy_f_bl vsip_vcopy_d_si vsip_vcopy_d_bl vsip_vcopy_i_f vsip_vcopy_i_d vsip_vcopy_i_i vsip_vcopy_i_si vsip_vcopy_i_vi vsip_vcopy_si_f vsip_vcopy_si_d vsip_vcopy_si_i vsip_vcopy_si_si vsip_vcopy_bl_f vsip_vcopy_bl_d vsip_vcopy_bl_bl vsip_vcopy_vi_i vsip_vcopy_vi_vi vsip_vcopy_mi_mi vsip_cvcopy_f_f vsip_cvcopy_f_d vsip_cvcopy_d_f vsip_cvcopy_d_d</pre>

Prototype	Description
<pre>void vsip_Dmcopy_P_P(const vsip_Dmview_P * A, const vsip_Dmview_P * R);</pre>	<p>Copy the source matrix to the destination matrix performing any necessary type conversion of the standard ANSI C scalar types.</p> <p>The following instances are supported:</p> <pre>vsip_mcopy_f_f vsip_mcopy_f_d vsip_mcopy_d_f vsip_mcopy_d_d vsip_mcopy_f_i vsip_mcopy_f_si vsip_mcopy_f_bl vsip_mcopy_d_i vsip_mcopy_d_si vsip_mcopy_d_bl vsip_mcopy_i_f vsip_mcopy_i_d vsip_mcopy_i_i vsip_mcopy_i_si vsip_mcopy_si_f vsip_mcopy_si_d vsip_mcopy_si_i vsip_mcopy_si_si vsip_mcopy_bl_f vsip_mcopy_bl_d vsip_mcopy_bl_bl vsip_cmcopy_f_f vsip_cmcopy_f_d vsip_cmcopy_d_f vsip_cmcopy_d_d</pre>
<pre>void vsip_Dvfill_P(const vsip_Dscalar_P a, const vsip_Dvview_P * R);</pre>	<p>Fill a vector with a constant value.</p> <p>The following instances are supported:</p> <pre>vsip_vfill_f vsip_vfill_d vsip_vfill_i vsip_vfill_si vsip_cvfill_f vsip_cvfill_d</pre>
<pre>void vsip_Dmfill_P(const vsip_Dscalar_P a, const vsip_Dmview_P * R);</pre>	<p>Fill a matrix with a constant value.</p> <p>The following instances are supported:</p> <pre>vsip_mfill_f vsip_mfill_d vsip_mfill_i vsip_mfill_si vsip_cmfill_f vsip_cmfill_d</pre>
<pre>void vsip_vramp_P(const vsip_scalar_P alpha, const vsip_scalar_P beta, const vsip_vview_P * R);</pre>	<p>Computes a vector ramp by starting at an initial value and incrementing each successive element by the ramp step size.</p> <p>The following instances are supported:</p> <pre>vsip_vramp_f vsip_vramp_d vsip_vramp_i vsip_vramp_si</pre>

4.9 Manipulation Operations

Prototype	Description
<pre>void vsip_vcmlx_P(const vsip_vview_P * A, const vsip_vview_P * B, const vsip_cvview_P * R);</pre>	<p>Form a complex vector from two real vectors.</p> <p>The following instances are supported:</p> <p>vsip_vcmlx_f vsip_vcmlx_d</p>
<pre>void vsip_mcmplx_P(const vsip_mview_P * A, const vsip_mview_P * B, const vsip_cmview_P * R);</pre>	<p>Form a complex matrix from two real matrices.</p> <p>The following instances are supported:</p> <p>vsip_mcmplx_f vsip_mcmplx_d</p>
<pre>void vsip_Dvgather_P(const vsip_Dvview_P * X, const vsip_vview_vi * I, const vsip_Dvview_P * Y);</pre>	<p>The gather operation selects elements of a source vector using indices supplied by an index vector. The selected elements are placed sequentially in an output vector so that the output vector and the index vector are indexed the same.</p> <p>The following instances are supported:</p> <p>vsip_vgather_f vsip_vgather_d vsip_vgather_i vsip_vgather_si vsip_cvgather_f vsip_cvgather_d</p>
<pre>void vsip_Dmgather_P(const vsip_Dmview_P * X, const vsip_vview_mi * I, const vsip_Dvview_P * Y);</pre>	<p>The gather operation selects elements of a source vector/matrix using indices supplied by an index vector. The selected elements are placed sequentially in an output vector so that the output vector and the index vector are indexed the same.</p> <p>The following instances are supported:</p> <p>vsip_mgather_f vsip_mgather_d vsip_mgather_i vsip_mgather_si vsip_cmgather_f vsip_cmgather_d</p>
<pre>void vsip_vimag_P(const vsip_cvview_P * A, const vsip_vview_P * R);</pre>	<p>Extract the imaginary part of a complex vector.</p> <p>The following instances are supported:</p> <p>vsip_vimag_f vsip_vimag_d</p>
<pre>void vsip_mimag_P(const vsip_cmview_P * A, const vsip_mview_P * R);</pre>	<p>Extract the imaginary part of a complex matrix.</p> <p>The following instances are supported:</p> <p>vsip_mimag_f vsip_mimag_d</p>

Prototype	Description
<pre>void vsip_vpolar_P(const vsip_cvview_P * A, const vsip_vview_P * R, const vsip_vview_P * P);</pre>	<p>Convert a complex vector from rectangular to polar form. The polar data consists of a real vector containing the radius and a corresponding real vector containing the argument (angle) of the complex input data.</p> <p>The following instances are supported:</p> <pre>vsip_vpolar_f vsip_vpolar_d</pre>
<pre>void vsip_mpolar_P(const vsip_cmview_P * A, const vsip_mview_P * R, const vsip_mview_P * P);</pre>	<p>Convert a complex matrix from rectangular to polar form. The polar data consists of a real matrix containing the radius and a corresponding real matrix containing the argument (angle) of the complex input data.</p> <p>The following instances are supported:</p> <pre>vsip_mpolar_f vsip_mpolar_d</pre>
<pre>void vsip_vreal_P(const vsip_cvview_P * A, const vsip_vview_P * R);</pre>	<p>Extract the real part of a complex vector.</p> <p>The following instances are supported:</p> <pre>vsip_vreal_f vsip_vreal_d</pre>
<pre>void vsip_mreal_P(const vsip_cmview_P * A, const vsip_mview_P * R);</pre>	<p>Extract the real part of a complex matrix.</p> <p>The following instances are supported:</p> <pre>vsip_mreal_f vsip_mreal_d</pre>
<pre>void vsip_vrect_P(const vsip_vview_P * R, const vsip_vview_P * P, const vsip_cvview_P * A);</pre>	<p>Convert a pair of real vectors from complex polar to complex rectangular form.</p> <p>The following instances are supported:</p> <pre>vsip_vrect_f vsip_vrect_d</pre>
<pre>void vsip_mrect_P(const vsip_mview_P * R, const vsip_mview_P * P, const vsip_cmview_P * A);</pre>	<p>Convert a pair of real matrices from complex polar to complex rectangular form.</p> <p>The following instances are supported:</p> <pre>vsip_mrect_f vsip_mrect_d</pre>
<pre>void vsip_Dvscatter_P(const vsip_Dvview_P * X, const vsip_Dvview_P * Y, const vsip_vview_vi * I);</pre>	<p>The scatter operation sequentially uses elements of a source vector and an index vector. The element of the vector index is used to select a storage location in the output vector to store the element from the source vector.</p> <p>The following instances are supported:</p> <pre>vsip_vscatter_f vsip_vscatter_d vsip_vscatter_i vsip_vscatter_si vsip_cvscatter_f vsip_cvscatter_d</pre>

Prototype	Description
<pre>void vsip_Dmscatter_P(const vsip_Dvview_P * X, const vsip_Dmview_P * Y, const vsip_vvview_mi * I);</pre>	<p>The scatter operation sequentially uses elements of a source vector and an index vector. The element of the vector/matrix index is used to select a storage location in the output vector/matrix to store the element from the source vector.</p> <p>The following instances are supported:</p> <pre>vsip_mscatter_f vsip_mscatter_d vsip_mscatter_i vsip_mscatter_si vsip_cmscatter_f vsip_cmscatter_d</pre>
<pre>void vsip_Dvswap_P(const vsip_Dvview_P * A, const vsip_Dvview_P * B);</pre>	<p>Swap elements between two vectors.</p> <p>The following instances are supported:</p> <pre>vsip_vswap_f vsip_vswap_d vsip_vswap_i vsip_vswap_si vsip_cvswap_f vsip_cvswap_d</pre>
<pre>void vsip_Dmswap_P(const vsip_Dmview_P * A, const vsip_Dmview_P * B);</pre>	<p>Swap elements between two matrices.</p> <p>The following instances are supported:</p> <pre>vsip_mswap_f vsip_mswap_d vsip_mswap_i vsip_mswap_si vsip_cmswap_f vsip_cmswap_d</pre>

4.10 Extensions

Prototype	Description
<pre>vsip_scalar_P vsip_Dsummgval_P(const vsip_Dvview_P * A);</pre>	<p>Returns the sum of the magnitude of elements of a vector.</p> <p>The following instances are supported:</p> <pre>vsip_vcsummgval_f vsip_vcsummgval_d</pre>

Chapter 5. Signal Processing Functions

5.1 FFT Functions

Prototype	Description
<pre><i>vsip_fft_P</i> * vsip_ccfftip_create_P(const <i>vsip_index</i> length, const <i>vsip_scalar_P</i> scale, const <i>vsip_fft_dir</i> dir, const <i>vsip_length</i> ntimes, const <i>vsip_alg_hint</i> hint);</pre>	Create a 1D FFT object. The following instances are supported: <code>vsip_ccfftip_create_f</code> <code>vsip_ccfftip_create_d</code>
<pre><i>vsip_fft_P</i> * vsip_ccfftop_create_P(const <i>vsip_index</i> length, const <i>vsip_scalar_P</i> scale, const <i>vsip_fft_dir</i> dir, const <i>vsip_length</i> ntimes, const <i>vsip_alg_hint</i> hint);</pre>	Create a 1D FFT object. The following instances are supported: <code>vsip_ccfftop_create_f</code> <code>vsip_ccfftop_create_d</code>
<pre><i>vsip_fft_P</i> * vsip_crfftop_create_P(const <i>vsip_index</i> length, const <i>vsip_scalar_P</i> scale, const <i>vsip_length</i> ntimes, const <i>vsip_alg_hint</i> hint);</pre>	Create a 1D FFT object. The following instances are supported: <code>vsip_crfftop_create_f</code> <code>vsip_crfftop_create_d</code>
<pre><i>vsip_fft_P</i> * vsip_rcfftop_create_P(const <i>vsip_index</i> length, const <i>vsip_scalar_P</i> scale, const <i>vsip_length</i> ntimes, const <i>vsip_alg_hint</i> hint);</pre>	Create a 1D FFT object. The following instances are supported: <code>vsip_rcfftop_create_f</code> <code>vsip_rcfftop_create_d</code>
<pre><i>int</i> vsip_fft_destroy_P(<i>vsip_fft_P</i> * plan);</pre>	Destroy an FFT object. The following instances are supported: <code>vsip_fft_destroy_f</code> <code>vsip_fft_destroy_d</code>
<pre><i>void</i> vsip_fft_getattr_P(const <i>vsip_fft_P</i> * plan, <i>vsip_fft_attr_P</i> * attr);</pre>	Return the attributes of an FFT object. The following instances are supported: <code>vsip_fft_getattr_f</code> <code>vsip_fft_getattr_d</code>
<pre><i>void</i> vsip_ccfftip_P(const <i>vsip_fft_P</i> * plan, const <i>vsip_cvview_P</i> * xy);</pre>	Apply a complex-to-complex Fast Fourier Transform (FFT). The following instances are supported: <code>vsip_ccfftip_f</code> <code>vsip_ccfftip_d</code>
<pre><i>void</i> vsip_ccfftop_P(const <i>vsip_fft_P</i> * plan, const <i>vsip_cvview_P</i> * x, const <i>vsip_cvview_P</i> * y);</pre>	Apply a complex-to-complex Fast Fourier Transform (FFT). The following instances are supported: <code>vsip_ccfftop_f</code> <code>vsip_ccfftop_d</code>

Prototype	Description
<pre>void vsip_crffftop_P(const vsip_fft_P * plan, const vsip_cvview_P * x, const vsip_vview_P * y);</pre>	<p>Apply a complex-to-real Fast Fourier Transform (FFT).</p> <p>The following instances are supported:</p> <p><code>vsip_crffftop_f</code> <code>vsip_crffftop_d</code></p>
<pre>void vsip_rcffftop_P(const vsip_fft_P * plan, const vsip_vview_P * x, const vsip_cvview_P * y);</pre>	<p>Apply a real-to-complex Fast Fourier Transform (FFT).</p> <p>The following instances are supported:</p> <p><code>vsip_rcffftop_f</code> <code>vsip_rcffftop_d</code></p>
<pre>vsip_fftm_P * vsip_ccfftmip_create_P(const vsip_index rows, const vsip_index cols, const vsip_scalar_P scale, const vsip_fft_dir dir, const vsip_major major, const vsip_length ntimes, const vsip_alg_hint hint);</pre>	<p>Create a 1D multiple FFT object.</p> <p>The following instances are supported:</p> <p><code>vsip_ccfftmip_create_f</code> <code>vsip_ccfftmip_create_d</code></p>
<pre>vsip_fftm_P * vsip_ccfftmop_create_P(const vsip_index rows, const vsip_index cols, const vsip_scalar_P scale, const vsip_fft_dir dir, const vsip_major major, const vsip_length ntimes, const vsip_alg_hint hint);</pre>	<p>Create a 1D multiple FFT object.</p> <p>The following instances are supported:</p> <p><code>vsip_ccfftmop_create_f</code> <code>vsip_ccfftmop_create_d</code></p>
<pre>vsip_fftm_P * vsip_crfftmop_create_P(const vsip_index rows, const vsip_index cols, const vsip_scalar_P scale, const vsip_major major, const vsip_length ntimes, const vsip_alg_hint hint);</pre>	<p>Create a 1D multiple FFT object.</p> <p>The following instances are supported:</p> <p><code>vsip_crfftmop_create_f</code> <code>vsip_crfftmop_create_d</code></p>
<pre>vsip_fftm_P * vsip_rcfftmop_create_P(const vsip_index rows, const vsip_index cols, const vsip_scalar_P scale, const vsip_major major, const vsip_length ntimes, const vsip_alg_hint hint);</pre>	<p>Create a 1D multiple FFT object.</p> <p>The following instances are supported:</p> <p><code>vsip_rcfftmop_create_f</code> <code>vsip_rcfftmop_create_d</code></p>
<pre>int vsip_fftm_destroy_P(vsip_fftm_P * plan);</pre>	<p>Destroy an FFT object.</p> <p>The following instances are supported:</p> <p><code>vsip_fftm_destroy_f</code> <code>vsip_fftm_destroy_d</code></p>
<pre>void vsip_fftm_getattr_P(const vsip_fftm_P * plan, vsip_fftm_attr_P * attr);</pre>	<p>Return the attributes of an FFT object.</p> <p>The following instances are supported:</p> <p><code>vsip_fftm_getattr_f</code> <code>vsip_fftm_getattr_d</code></p>

Prototype	Description
<pre>void vsip_ccfftmip_P(const vsip_fftm_P * plan, const vsip_cmview_P * XY);</pre>	<p>Apply a multiple complex-to-complex Fast Fourier Transform (FFT). The following instances are supported:</p> <p>vsip_ccfftmip_f vsip_ccfftmip_d</p>
<pre>void vsip_ccfftmop_P(const vsip_fftm_P * plan, const vsip_cmview_P * X, const vsip_cmview_P * Y);</pre>	<p>Apply a multiple complex-to-complex Fast Fourier Transform (FFT). The following instances are supported:</p> <p>vsip_ccfftmop_f vsip_ccfftmop_d</p>
<pre>void vsip_crfftmop_P(const vsip_fftm_P * plan, const vsip_cmview_P * X, const vsip_mview_P * Y);</pre>	<p>Apply a multiple complex-to-real Fast Fourier Transform (FFT). The following instances are supported:</p> <p>vsip_crfftmop_f vsip_crfftmop_d</p>
<pre>void vsip_rcfftmop_P(const vsip_fftm_P * plan, const vsip_mview_P * X, const vsip_cmview_P * Y);</pre>	<p>Apply a multiple real-to-complex out of place Fast Fourier Transform (FFT). The following instances are supported:</p> <p>vsip_rcfftmop_f vsip_rcfftmop_d</p>
<pre>vsip_fft2d_P * vsip_ccfft2dip_create_P(const vsip_index rows, const vsip_index cols, const vsip_scalar_P scale, const vsip_fft_dir dir, const vsip_length ntimes, const vsip_alg_hint hint);</pre>	<p>Create a 2D FFT object. The following instances are supported:</p> <p>vsip_ccfft2dip_create_f vsip_ccfft2dip_create_d</p>
<pre>vsip_fft2d_P * vsip_ccfft2dop_create_P(const vsip_index rows, const vsip_index cols, const vsip_scalar_P scale, const vsip_fft_dir dir, const vsip_length ntimes, const vsip_alg_hint hint);</pre>	<p>Create a 2D FFT object. The following instances are supported:</p> <p>vsip_ccfft2dop_create_f vsip_ccfft2dop_create_d</p>
<pre>vsip_fft2d_P * vsip_crfft2dop_create_P(const vsip_index rows, const vsip_index cols, const vsip_scalar_P scale, const vsip_length ntimes, const vsip_alg_hint hint);</pre>	<p>Create a 2D FFT object. The following instances are supported:</p> <p>vsip_crfft2dop_create_f vsip_crfft2dop_create_d</p>
<pre>vsip_fft2d_P * vsip_rcfft2dop_create_P(const vsip_index rows, const vsip_index cols, const vsip_scalar_P scale, const vsip_length ntimes, const vsip_alg_hint hint);</pre>	<p>Create a 2D FFT object. The following instances are supported:</p> <p>vsip_rcfft2dop_create_f vsip_rcfft2dop_create_d</p>
<pre>int vsip_fft2d_destroy_P(vsip_fft2d_P * plan);</pre>	<p>Destroy an FFT object. The following instances are supported:</p> <p>vsip_fft2d_destroy_f vsip_fft2d_destroy_d</p>

Prototype	Description
<pre>void vsip_fft2d_getattr_P(const vsip_fft2d_P * plan, vsip_fft2d_attr_P * attr);</pre>	<p>Return the attributes of an FFT object. The following instances are supported:</p> <p><code>vsip_fft2d_getattr_f</code> <code>vsip_fft2d_getattr_d</code></p>
<pre>void vsip_ccfft2dip_P(const vsip_fft2d_P * plan, const vsip_cmview_P * XY);</pre>	<p>Apply a complex-to-complex 2D Fast Fourier Transform (FFT). The following instances are supported:</p> <p><code>vsip_ccfft2dip_f</code> <code>vsip_ccfft2dip_d</code></p>
<pre>void vsip_ccfft2dop_P(const vsip_fft2d_P * plan, const vsip_cmview_P * X, const vsip_cmview_P * Y);</pre>	<p>Apply a complex-to-complex 2D Fast Fourier Transform (FFT). The following instances are supported:</p> <p><code>vsip_ccfft2dop_f</code> <code>vsip_ccfft2dop_d</code></p>
<pre>void vsip_crfft2dop_P(const vsip_fft2d_P * plan, const vsip_cmview_P * X, const vsip_mview_P * Y);</pre>	<p>Apply a complex-to-real 2D Fast Fourier Transform (FFT). The following instances are supported:</p> <p><code>vsip_crfft2dop_f</code> <code>vsip_crfft2dop_d</code></p>
<pre>void vsip_rcfft2dop_P(const vsip_fft2d_P * plan, const vsip_mview_P * X, const vsip_cmview_P * Y);</pre>	<p>Apply a real-to-complex 2D Fast Fourier Transform (FFT). The following instances are supported:</p> <p><code>vsip_rcfft2dop_f</code> <code>vsip_rcfft2dop_d</code></p>

5.2 Convolution/Correlation Functions

Prototype	Description
<pre>vsip_conv1d_P * vsip_conv1d_create_P(const vsip_vview_P * kernel, const vsip_symmetry symm, const vsip_length N, const vsip_length D, const vsip_support_region support, const vsip_length ntimes, const vsip_alg_hint hint);</pre>	<p>Create a decimated 1D convolution filter object.</p> <p>The following instances are supported:</p> <pre>vsip_conv1d_create_f vsip_conv1d_create_d</pre>
<pre>int vsip_conv1d_destroy_P(vsip_conv1d_P * plan);</pre>	<p>Destroy a 1D convolution object.</p> <p>The following instances are supported:</p> <pre>vsip_conv1d_destroy_f vsip_conv1d_destroy_d</pre>
<pre>void vsip_conv1d_getattr_P(const vsip_conv1d_P * plan, vsip_conv1d_attr_P * attr);</pre>	<p>Returns the attributes for a 1D convolution object.</p> <p>The following instances are supported:</p> <pre>vsip_conv1d_getattr_f vsip_conv1d_getattr_d</pre>
<pre>void vsip_convolve1d_P(const vsip_conv1d_P * plan, const vsip_vview_P * x, const vsip_vview_P * y);</pre>	<p>Compute a decimated real one-dimensional (1D) convolution of two vectors.</p> <p>The following instances are supported:</p> <pre>vsip_convolve1d_f vsip_convolve1d_d</pre>
<pre>vsip_conv2d_P * vsip_conv2d_create_P(const vsip_mview_P * H, const vsip_symmetry symm, const vsip_length P, const vsip_length Q, const vsip_length D, const vsip_support_region support, const vsip_length ntimes, const vsip_alg_hint hint);</pre>	<p>Create a decimated 2D convolution filter object.</p> <p>The following instances are supported:</p> <pre>vsip_conv2d_create_f vsip_conv2d_create_d</pre>
<pre>int vsip_conv2d_destroy_P(vsip_conv2d_P * plan);</pre>	<p>Destroy a 2D convolution object.</p> <p>The following instances are supported:</p> <pre>vsip_conv2d_destroy_f vsip_conv2d_destroy_d</pre>
<pre>void vsip_conv2d_getattr_P(const vsip_conv2d_P * plan, vsip_conv2d_attr_P * attr);</pre>	<p>Returns the attributes for a 2D convolution object.</p> <p>The following instances are supported:</p> <pre>vsip_conv2d_getattr_f vsip_conv2d_getattr_d</pre>
<pre>void vsip_convolve2d_P(const vsip_conv2d_P * plan, const vsip_mview_P * x, const vsip_mview_P * y);</pre>	<p>Compute a decimated real two-dimensional (2D) convolution of two matrices.</p> <p>The following instances are supported:</p> <pre>vsip_convolve2d_f vsip_convolve2d_d</pre>

Prototype	Description
<pre>vsip_Dcorr1d_P * vsip_Dcorr1d_create_P(const vsip_length M, const vsip_length N, const vsip_support_region support, const vsip_length ntimes, const vsip_alg_hint hint);</pre>	<p>Create a 1D correlation object. The following instances are supported:</p> <pre>vsip_corr1d_create_f vsip_corr1d_create_d vsip_ccorr1d_create_f vsip_ccorr1d_create_d</pre>
<pre>int vsip_Dcorr1d_destroy_P(vsip_Dcorr1d_P * plan);</pre>	<p>Destroy a 1D correlation object. The following instances are supported:</p> <pre>vsip_corr1d_destroy_f vsip_corr1d_destroy_d vsip_ccorr1d_destroy_f vsip_ccorr1d_destroy_d</pre>
<pre>void vsip_Dcorr1d_getattr_P(const vsip_Dcorr1d_P * plan, vsip_Dcorr1d_attr_P * attr);</pre>	<p>Return the attributes for a 1D correlation object. The following instances are supported:</p> <pre>vsip_corr1d_getattr_f vsip_corr1d_getattr_d vsip_ccorr1d_getattr_f vsip_ccorr1d_getattr_d</pre>
<pre>void vsip_Dcorrelate1d_P(const vsip_Dcorr1d_P * plan, const vsip_bias bias, const vsip_Dvview_P * ref, const vsip_Dvview_P * x, const vsip_Dvview_P * y);</pre>	<p>Compute a real one-dimensional (1D) correlation of two vectors. The following instances are supported:</p> <pre>vsip_correlate1d_f vsip_correlate1d_d vsip_ccorrelate1d_f vsip_ccorrelate1d_d</pre>
<pre>vsip_Dcorr2d_P * vsip_Dcorr2d_create_P(const vsip_length M, const vsip_length N, vsip_length P, vsip_length Q, const vsip_support_region support, const vsip_length ntimes, const vsip_alg_hint hint);</pre>	<p>Create a 2D correlation object. The following instances are supported:</p> <pre>vsip_corr2d_create_f vsip_corr2d_create_d vsip_ccorr2d_create_f vsip_ccorr2d_create_d</pre>
<pre>int vsip_Dcorr2d_destroy_P(vsip_Dcorr2d_P * plan);</pre>	<p>Destroy a 2D correlation object. The following instances are supported:</p> <pre>vsip_corr2d_destroy_f vsip_corr2d_destroy_d vsip_ccorr2d_destroy_f vsip_ccorr2d_destroy_d</pre>
<pre>void vsip_Dcorr2d_getattr_P(const vsip_Dcorr2d_P * plan, vsip_Dcorr2d_attr_P * attr);</pre>	<p>Return the attributes for a 2D correlation object. The following instances are supported:</p> <pre>vsip_corr2d_getattr_f vsip_corr2d_getattr_d vsip_ccorr2d_getattr_f vsip_ccorr2d_getattr_d</pre>

Prototype	Description
<pre>void vsip_Dcorrelate2d_P(const vsip_Dcorr2d_P * plan, const vsip_bias bias, const vsip_Dmview_P * ref, const vsip_Dmview_P * x, const vsip_Dmview_P * y);</pre>	<p>Compute a two-dimensional (2D) correlation of two matrices.</p> <p>The following instances are supported:</p> <pre>vsip_correlate2d_f vsip_correlate2d_d vsip_ccorrelate2d_f vsip_ccorrelate2d_d</pre>

5.3 Window Functions

Prototype	Description
<pre>vsip_vview_P * vsip_vcreate_blackman_P(const vsip_length N, const vsip_memory_hint hint);</pre>	<p>Create a vector with Blackman window weights.</p> <p>The following instances are supported:</p> <pre>vsip_vcreate_blackman_f vsip_vcreate_blackman_d</pre>
<pre>vsip_vview_P * vsip_vcreate_cheby_P(const vsip_length N, const vsip_scalar_P ripple, const vsip_memory_hint hint);</pre>	<p>Create a vector with Dolph-Chebyshev window weights.</p> <p>The following instances are supported:</p> <pre>vsip_vcreate_cheby_f vsip_vcreate_cheby_d</pre>
<pre>vsip_vview_P * vsip_vcreate_hanning_P(const vsip_length N, const vsip_memory_hint hint);</pre>	<p>Create a vector with Hanning window weights.</p> <p>The following instances are supported:</p> <pre>vsip_vcreate_hanning_f vsip_vcreate_hanning_d</pre>
<pre>vsip_vview_P * vsip_vcreate_kaiser_P(const vsip_length N, const vsip_scalar_P beta, const vsip_memory_hint hint);</pre>	<p>Create a vector with Kaiser window weights.</p> <p>The following instances are supported:</p> <pre>vsip_vcreate_kaiser_f vsip_vcreate_kaiser_d</pre>

5.4 Filter Functions

Prototype	Description
<pre>vsip_Dfir_P * vsip_Dfir_create_P(const vsip_Dvview_P * kernel, const vsip_symmetry symm, const vsip_length N, const vsip_length D, const vsip_obj_state state, const vsip_length ntimes, const vsip_alg_hint hint);</pre>	<p>Create a decimated FIR filter object.</p> <p>The following instances are supported:</p> <pre>vsip_fir_create_f vsip_fir_create_d vsip_cfir_create_f vsip_cfir_create_d</pre>

Prototype	Description
<pre>int vsip_Dfir_destroy_P(vsip_Dfir_P * plan);</pre>	<p>Destroy a FIR filter object. The following instances are supported:</p> <pre>vsip_fir_destroy_f vsip_fir_destroy_d vsip_cfir_destroy_f vsip_cfir_destroy_d</pre>
<pre>int vsip_Dfirflt_P(vsip_Dfir_P * plan, const vsip_Dvview_P * x, const vsip_Dvview_P * y);</pre>	<p>FIR filter an input sequence and decimate the output. The following instances are supported:</p> <pre>vsip_firflt_f vsip_firflt_d vsip_cfirflt_f vsip_cfirflt_d</pre>
<pre>void vsip_Dfir_getattr_P(const vsip_Dfir_P * plan, vsip_Dfir_attr_P * attr);</pre>	<p>Return the attributes of a FIR filter object. The following instances are supported:</p> <pre>vsip_fir_getattr_f vsip_fir_getattr_d vsip_cfir_getattr_f vsip_cfir_getattr_d</pre>
<pre>void vsip_Dfir_reset_P(vsip_Dfir_P * fir);</pre>	<p>Reset the state of a decimated FIR filter object. The following instances are supported:</p> <pre>vsip_fir_reset_f vsip_fir_reset_d vsip_cfir_reset_f vsip_cfir_reset_d</pre>

5.5 Miscellaneous signal Processing Functions

Prototype	Description
<pre>void vsip_vhisto_P(const vsip_vview_P * A, const vsip_scalar_P min, const vsip_scalar_P max, const vsip_hist_opt opt, const vsip_vview_P * R);</pre>	<p>Compute the histogram of a vector. The following instances are supported:</p> <pre>vsip_vhisto_f vsip_vhisto_d</pre>

Chapter 6. Linear Algebra

6.1 Matrix and Vector Operations

Prototype	Description
<pre>void vsip_cmherm_P(const vsip_cmview_P * A, const vsip_cmview_P * R);</pre>	Complex Hermitian (conjugate transpose) of a matrix. The following instances are supported: <code>vsip_cmherm_f</code> <code>vsip_cmherm_d</code>
<pre>vsip_cscalar_P vsip_cvjdot_P(const vsip_cvview_P * A, const vsip_cvview_P * B);</pre>	Compute the conjugate inner (dot) product of two complex vectors. The following instances are supported: <code>vsip_cvjdot_f</code> <code>vsip_cvjdot_d</code>
<pre>void vsip_gemp_P(const vsip_scalar_P alpha, const vsip_mview_P * A, const vsip_mat_op Aop, const vsip_mview_P * B, const vsip_mat_op Bop, const vsip_scalar_P beta, const vsip_mview_P * R);</pre>	Calculate the general product of two matrices and accumulate. The following instances are supported: <code>vsip_gemp_f</code> <code>vsip_gemp_d</code>
<pre>void vsip_cgemp_P(const vsip_cscalar_P alpha, const vsip_cmview_P * A, const vsip_mat_op Aop, const vsip_cmview_P * B, const vsip_mat_op Bop, const vsip_cscalar_P beta, const vsip_cmview_P * R);</pre>	Calculate the general product of two matrices and accumulate. The following instances are supported: <code>vsip_cgemp_f</code> <code>vsip_cgemp_d</code>
<pre>void vsip_gems_P(const vsip_scalar_P alpha, const vsip_mview_P * A, const vsip_mat_op Aop, const vsip_scalar_P beta, const vsip_mview_P * C);</pre>	Calculate a general matrix sum. The following instances are supported: <code>vsip_gems_f</code> <code>vsip_gems_d</code>
<pre>void vsip_cgems_P(const vsip_cscalar_P alpha, const vsip_cmview_P * A, const vsip_mat_op Aop, const vsip_cscalar_P beta, const vsip_cmview_P * C);</pre>	Calculate a general matrix sum. The following instances are supported: <code>vsip_cgems_f</code> <code>vsip_cgems_d</code>

Prototype	Description
<pre>void vsip_Dmprod_P(const vsip_Dmview_P * A, const vsip_Dmview_P * B, const vsip_Dmview_P * R);</pre>	<p>Calculate the product of two matrices. The following instances are supported:</p> <pre>vsip_mprod_f vsip_mprod_d vsip_mprod_i vsip_mprod_si vsip_cmprod_f vsip_cmprod_d vsip_cmprod_i vsip_cmprod_si</pre>
<pre>void vsip_cmprodh_P(const vsip_cmview_P * A, const vsip_cmview_P * B, const vsip_cmview_P * R);</pre>	<p>Calculate the product a complex matrix and the Hermitian of a complex matrix. The following instances are supported:</p> <pre>vsip_cmprodh_f vsip_cmprodh_d vsip_cmprodh_i vsip_cmprodh_si</pre>
<pre>void vsip_cmprodj_P(const vsip_cmview_P * A, const vsip_cmview_P * B, const vsip_cmview_P * R);</pre>	<p>Calculate the product a complex matrix and the conjugate of a complex matrix. The following instances are supported:</p> <pre>vsip_cmprodj_f vsip_cmprodj_d vsip_cmprodj_i vsip_cmprodj_si</pre>
<pre>void vsip_Dmprodt_P(const vsip_Dmview_P * A, const vsip_Dmview_P * B, const vsip_Dmview_P * R);</pre>	<p>Calculate the product of a matrix and the transpose of a matrix. The following instances are supported:</p> <pre>vsip_mprodt_f vsip_mprodt_d vsip_mprodt_i vsip_mprodt_si vsip_cmprodt_f vsip_cmprodt_d vsip_cmprodt_i vsip_cmprodt_si</pre>
<pre>void vsip_Dmvprod_P(const vsip_Dmview_P * A, const vsip_Dvview_P * X, const vsip_Dvview_P * Y);</pre>	<p>Calculate a matrix–vector product. The following instances are supported:</p> <pre>vsip_mvprod_f vsip_mvprod_d vsip_mvprod_i vsip_mvprod_si vsip_cmvprod_f vsip_cmvprod_d vsip_cmvprod_i vsip_cmvprod_si</pre>

Prototype	Description
<pre>void vsip_Dmtrans_P(const vsip_Dmview_P * A, const vsip_Dmview_P * R);</pre>	<p>Transpose a matrix. The following instances are supported:</p> <pre>vsip_mtrans_bl vsip_mtrans_f vsip_mtrans_d vsip_mtrans_i vsip_mtrans_si vsip_cmtrans_f vsip_cmtrans_d vsip_cmtrans_i vsip_cmtrans_si</pre>
<pre>vsip_Dscalar_P vsip_Dvdot_P(const vsip_Dvview_P * A, const vsip_Dvview_P * B);</pre>	<p>Compute the inner (dot) product of two vectors. The following instances are supported:</p> <pre>vsip_vdot_f vsip_vdot_d vsip_cvdot_f vsip_cvdot_d</pre>
<pre>void vsip_Dvmprod_P(const vsip_Dvview_P * X, const vsip_Dmview_P * A, const vsip_Dvview_P * Y);</pre>	<p>Calculate a vector–matrix product. The following instances are supported:</p> <pre>vsip_vmprod_f vsip_vmprod_d vsip_vmprod_i vsip_vmprod_si vsip_cvmprod_f vsip_cvmprod_d vsip_cvmprod_i vsip_cvmprod_si</pre>
<pre>void vsip_vouter_P(const vsip_scalar_P alpha, const vsip_vview_P * X, const vsip_vview_P * Y, const vsip_vview_P * R);</pre>	<p>Calculate the outer product of two vectors. The following instances are supported:</p> <pre>vsip_vouter_f vsip_vouter_d</pre>
<pre>void vsip_cvouter_P(const vsip_cscalar_P alpha, const vsip_cvview_P * X, const vsip_cvview_P * Y, const vsip_cvview_P * R);</pre>	<p>Calculate the outer product of two vectors. The following instances are supported:</p> <pre>vsip_cvouter_f vsip_cvouter_d</pre>

6.2 Special Linear System Solvers

Prototype	Description
<pre>int vsip_covsol_P(const vsip_mview_P * A, const vsip_mview_P * XB);</pre>	<p>Solve a covariance linear system problem. The following instances are supported:</p> <pre>vsip_covsol_f vsip_covsol_d</pre>

Prototype	Description
<pre>int vsip_ccovsol_P(const vsip_cmview_P * A, const vsip_cmview_P * XB);</pre>	<p>Solve a covariance linear system problem. The following instances are supported:</p> <p><code>vsip_ccovsol_f</code> <code>vsip_ccovsol_d</code></p>
<pre>int vsip_llsqsol_P(const vsip_mview_P * A, const vsip_mview_P * XB);</pre>	<p>Solve a linear least squares problem. The following instances are supported:</p> <p><code>vsip_llsqsol_f</code> <code>vsip_llsqsol_d</code></p>
<pre>int vsip_cllsqsol_P(const vsip_cmview_P * A, const vsip_cmview_P * XB);</pre>	<p>Solve a linear least squares problem. The following instances are supported:</p> <p><code>vsip_cllsqsol_f</code> <code>vsip_cllsqsol_d</code></p>
<pre>int vsip_toepsol_P(const vsip_vview_P * T, const vsip_vview_P * B, const vsip_vview_P * W, const vsip_vview_P * X);</pre>	<p>Solve a real symmetric positive definite Toeplitz linear system. The following instances are supported:</p> <p><code>vsip_toepsol_f</code> <code>vsip_toepsol_d</code></p>
<pre>int vsip_ctoepsol_P(const vsip_cvview_P * T, const vsip_cvview_P * B, const vsip_cvview_P * W, const vsip_cvview_P * X);</pre>	<p>Solve a real symmetric positive definite Toeplitz linear system. The following instances are supported:</p> <p><code>vsip_ctoepsol_f</code> <code>vsip_ctoepsol_d</code></p>

6.3 General Square Linear System Solver

Prototype	Description
<pre>int vsip_Dlud_P(vsip_clu_P * lud, const vsip_Dmview_P * A);</pre>	<p>Compute an LU decomposition of a square matrix using partial pivoting. The following instances are supported:</p> <p><code>vsip_lud_f</code> <code>vsip_lud_d</code> <code>vsip_clud_f</code> <code>vsip_clud_d</code></p>
<pre>vsip_Dlu_P * vsip_Dlud_create_P(const vsip_length N);</pre>	<p>Create an LU decomposition object. The following instances are supported:</p> <p><code>vsip_lud_create_f</code> <code>vsip_lud_create_d</code> <code>vsip_clud_create_f</code> <code>vsip_clud_create_d</code></p>
<pre>int vsip_Dlud_destroy_P(vsip_Dlu_P * lud);</pre>	<p>Destroy an LU decomposition object. The following instances are supported:</p> <p><code>vsip_lud_destroy_f</code> <code>vsip_lud_destroy_d</code> <code>vsip_clud_destroy_f</code> <code>vsip_clud_destroy_d</code></p>
<pre>void vsip_Dlud_getattr_P(const vsip_Dlu_P * lud, vsip_Dlu_attr_P * attr);</pre>	<p>Returns the attributes of an LU decomposition object. The following instances are supported:</p> <p><code>vsip_lud_getattr_f</code> <code>vsip_lud_getattr_d</code> <code>vsip_clud_getattr_f</code> <code>vsip_clud_getattr_d</code></p>
<pre>int vsip_lusol_P(const vsip_clu_P * clud, const vsip_mat_op opA, const vsip_mview_P * XB);</pre>	<p>Solve a square linear system. The following instances are supported:</p> <p><code>vsip_lusol_f</code> <code>vsip_lusol_d</code></p>
<pre>int vsip_clusol_P(const vsip_clu_P * clud, const vsip_mat_op opA, const vsip_cmview_P * XB);</pre>	<p>Solve a square linear system. The following instances are supported:</p> <p><code>vsip_clusol_f</code> <code>vsip_clusol_d</code></p>

6.4 Symmetric Positive Definite Linear System Solver

Prototype	Description
<pre>int vsip_chold_P(vsip_chol_P * chold, const vsip_mview_P * A);</pre>	<p>Compute a Cholesky decomposition of a symmetric positive definite matrix. The following instances are supported:</p> <p><code>vsip_chold_f</code> <code>vsip_chold_d</code></p>

Prototype	Description
<pre>int vsip_cchold_P(vsip_cchol_P * chold, const vsip_cmview_P * A);</pre>	<p>Compute a Cholesky decomposition of a symmetric positive definite matrix. The following instances are supported:</p> <p>vsip_cchold_f vsip_cchold_d</p>
<pre>vsip_chol_P * vsip_chold_create_P(const vsip_mat_uplo uplo, const vsip_length n);</pre>	<p>Creates a Cholesky decomposition object. The following instances are supported:</p> <p>vsip_chold_create_f vsip_chold_create_d</p>
<pre>vsip_cchol_P * vsip_cchold_create_P(const vsip_mat_uplo uplo, const vsip_length n);</pre>	<p>Creates a Cholesky decomposition object. The following instances are supported:</p> <p>vsip_cchold_create_f vsip_cchold_create_d</p>
<pre>int vsip_Dchold_destroy_P(vsip_Dchol_P * chold);</pre>	<p>Destroy a Cholesky decomposition object. The following instances are supported:</p> <p>vsip_chold_destroy_f vsip_chold_destroy_d vsip_cchold_destroy_f vsip_cchold_destroy_d</p>
<pre>void vsip_Dchold_getattr_P(const vsip_Dchol_P * chold, vsip_Dchol_attr_P * attr);</pre>	<p>Returns the attributes of a Cholesky decomposition object. The following instances are supported:</p> <p>vsip_chold_getattr_f vsip_chold_getattr_d vsip_cchold_getattr_f vsip_cchold_getattr_d</p>
<pre>int vsip_cholsol_P(const vsip_cchol_P * chold, const vsip_mview_P * XB);</pre>	<p>Solve a symmetric positive definite linear system. The following instances are supported:</p> <p>vsip_cholsol_f vsip_cholsol_d</p>
<pre>int vsip_ccholsol_P(const vsip_cchol_P * chold, const vsip_cmview_P * XB);</pre>	<p>Solve a symmetric positive definite linear system. The following instances are supported:</p> <p>vsip_ccholsol_f vsip_ccholsol_d</p>

6.5 Overdetermined Linear System Solver

Prototype	Description
<pre>int vsip_qrd_P(vsip_cqr_P * qrd, const vsip_mview_P * A);</pre>	<p>Compute a QR decomposition of a matrix. The following instances are supported:</p> <p>vsip_qrd_f vsip_qrd_d</p>

Prototype	Description
<pre>int vsip_cqrd_P(vsip_cqr_P * qrd, const vsip_cmview_P * A);</pre>	<p>Compute a QR decomposition of a matrix . The following instances are supported:</p> <p><code>vsip_cqrd_f</code> <code>vsip_cqrd_d</code></p>
<pre>vsip_qr_P * vsip_qrd_create_P(const vsip_length m, const vsip_length n, const vsip_qrd_qopt qopt);</pre>	<p>Create a QR decomposition object. The following instances are supported:</p> <p><code>vsip_qrd_create_f</code> <code>vsip_qrd_create_d</code></p>
<pre>vsip_cqr_P * vsip_cqrd_create_P(const vsip_length m, const vsip_length n, const vsip_qrd_qopt qopt);</pre>	<p>Create a QR decomposition object. The following instances are supported:</p> <p><code>vsip_cqrd_create_f</code> <code>vsip_cqrd_create_d</code></p>
<pre>int vsip_Dqrd_destroy_P(vsip_Dqr_P * qrd);</pre>	<p>Destroy a QR decomposition object. The following instances are supported:</p> <p><code>vsip_qrd_destroy_f</code> <code>vsip_qrd_destroy_d</code> <code>vsip_cqrd_destroy_f</code> <code>vsip_cqrd_destroy_d</code></p>
<pre>void vsip_Dqrd_getattr_P(const vsip_Dqr_P * qrd, vsip_Dqr_attr_P * attr);</pre>	<p>Returns the attributes of a QR decomposition object. The following instances are supported:</p> <p><code>vsip_qrd_getattr_f</code> <code>vsip_qrd_getattr_d</code> <code>vsip_cqrd_getattr_f</code> <code>vsip_cqrd_getattr_d</code></p>
<pre>int vsip_qrdprodq_P(const vsip_qr_P * qrd, const vsip_mat_op opQ, const vsip_mat_side apQ, const vsip_mview_P * C);</pre>	<p>Multiply a matrix by the matrix Q from a QR decomposition. The following instances are supported:</p> <p><code>vsip_qrdprodq_f</code> <code>vsip_qrdprodq_d</code></p>
<pre>int vsip_cqrdprodq_P(const vsip_cqr_P * qrd, const vsip_mat_op opQ, const vsip_mat_side apQ, const vsip_cmview_P * C);</pre>	<p>Multiply a matrix by the matrix Q from a QR decomposition. The following instances are supported:</p> <p><code>vsip_cqrdprodq_f</code> <code>vsip_cqrdprodq_d</code></p>
<pre>int vsip_qrdsolr_P(const vsip_qr_P * qrd, const vsip_mat_op OpR, const vsip_scalar_P alpha, const vsip_mview_P * XB);</pre>	<p>Solve linear system based on the matrix R, from QR decomposition of the matrix A. The following instances are supported:</p> <p><code>vsip_qrdsolr_f</code> <code>vsip_qrdsolr_d</code></p>
<pre>int vsip_cqrdsolr_P(const vsip_cqr_P * qrd, const vsip_mat_op OpR, const vsip_cscalar_P alpha, const vsip_cmview_P * XB);</pre>	<p>Solve linear system based on the matrix R, from QR decomposition of the matrix A. The following instances are supported:</p> <p><code>vsip_cqrdsolr_f</code> <code>vsip_cqrdsolr_d</code></p>

Prototype	Description
<pre>int vsip_qrsol_P(const vsip_qr_P * qrd, const vsip_mat_op OpR, const vsip_scalar_P alpha, const vsip_mview_P * XB);</pre>	<p>Solve linear system based on the matrix R, from QR decomposition of the matrix A. The following instances are supported:</p> <p><code>vsip_qrsol_f</code> <code>vsip_qrsol_d</code></p>
<pre>int vsip_cqrsol_P(const vsip_cqr_P * qrd, const vsip_qrd_prob prob, const vsip_cmview_P * XB);</pre>	<p>Solve either a linear covariance or linear least squares problem. The following instances are supported:</p> <p><code>vsip_cqrsol_f</code> <code>vsip_cqrsol_d</code></p>

6.6 Extensions

Prototype	Description
<pre>void vsip_Dminvlu_P(const vsip_Dmview_P * A, const vsip_vview_i * V, const vsip_Dmview_P * R);</pre>	<p>Invert a square matrix using LU decomposition. The following instances are supported:</p> <p><code>vsip_minvlu_f</code> <code>vsip_minvlu_d</code> <code>vsip_cminvlu_f</code> <code>vsip_cminvlu_d</code></p>